



216376
M22-K10

Overview

Specifications

Resources



Delivery program

Technical data

Design verification as per IEC/EN 61439

Technical data ETIM 7.0

Approvals

Dimensions

DELIVERY PROGRAM

Product range
Accessories

Basic function accessories
Contact elements

Accessories
Auxiliary contact

Accessories
Standard auxiliary contact, trip-indicating auxiliary switch

Standard/Approval
UL/CSA, IEC

Construction size
NZM1/2/3/4

Connection technique
Screw terminals

Fixing
Front fixing

Degree of Protection
IP20

Connection to SmartWire-DT
no

For use with
NZM1(-4), 2(-4), 3(-4), 4(-4)
FN1(-4), 2(-4), 3(-4)
N(S)1(-4), 2(-4), 3(-4), 4(-4)

Approval



Contacts

NO = Normally open
1 NO

Contact sequence




Contact travel diagram, stroke in connection with front element

Contact diagram



Configuration



Connection type
Single contact

Description of HIA trip-indicating auxiliary contact
General trip indication '+', when tripped by shunt release, overload release, short-circuit release or by the residual-current release due to residual-current.

Can be used with NZM1, 2, 3 circuit-breaker: a trip-indicating auxiliary contact can be clipped into the circuit-breaker.

Can be used with NZM4 circuit-breaker: up to two standard auxiliary contacts can be clipped into the circuit-breaker.

Any combinations of the auxiliary contact types are possible.

Not in combination with switch-disconnector FN...

Marking on switch: HIA

Labeling in FI-Block: HIAFI

If the trip-indicating auxiliary switch in the fault current block is used, the NC contacts operates as a NO contact and the NC contact operates as an NO contact.

Description standard auxiliary contact HIN

Switching with the main contacts Used for indicating and interlocking tasks.

Can be used with NZM1 circuit-breaker: a standard auxiliary contact can be clipped into the circuit-breaker.

Can be used with NZM2 size circuit-breaker: a standard auxiliary contact can be clipped into the circuit-breaker.

Can be used with NZM3, 4 circuit-breaker: up to three standard auxiliary contacts can be clipped into the circuit-breaker.

Any combinations of the auxiliary contact types are possible.

Marking on switch: HIN

On combination with remote operator NZM-XR... the right mounting location of standard auxiliary contact HIN can be fitted only with individual contacts.

Connection technique

Screw terminals

Notes

For Std. pack:

M22-(C)K... : Std. pack = 20 off

Notes

The following can be clipped into the switches:

- NZM1: a standard auxiliary contact
- NZM2: up to two M22-(C)K... standard auxiliary contacts
- NZM3: up to three M22-(C)K... standard auxiliary contacts
- NZM4: up to three M22-(C)K... standard

auxiliary contacts

Any combinations of the auxiliary contact types are possible.

Marking on switch: H1N

In combination with remote operator NZM-XR... only single contacts can be fitted to some installation locations of the standard auxiliary contact.

NZM2: Only single contact can be fitted in left installation location of standard auxiliary contact.

NZM3: Only single contact can be fitted in installation locations of standard auxiliary contact.

NZM4: Only single contact can be fitted in right installation location of standard auxiliary contact.

TECHNICAL DATA

General

Standards
IEC 60947-5-1

Lifespan, mechanical [Operations]
> 5 x 10⁶

Operating frequency [Operations/h]
 3600

Actuating force
 5 n

Operating torque (screw terminals)
 0.8 Nm

Degree of Protection
IP20

Climatic proofing
Damp heat, constant, to IEC 60068-2-78
Damp heat, cyclic, to IEC 60068-2-30

Ambient temperature
Open
-25 - +70 °C

Mechanical shock resistance to IEC 60068-2-27
Shock duration 11 ms, half-sinusoidal
> 30 g

Terminal capacities
Solid
0.75 - 2.5 mm²

Terminal capacities
Stranded
0.5 - 2.5 mm²

Terminal capacities
Flexible with ferrule
0.5 - 1.5 mm²

Contacts

Rated impulse withstand voltage [U_{imp}]
6000 V AC

Rated insulation voltage [U_i]
500 V

Overvoltage category/pollution degree
III/3

Control circuit reliability
at 24 V DC/5 mA [H_F]
< 10⁻⁷ (i.e. 1 failure to 10⁷ operations) Fault
probability

Control circuit reliability
at 5 V DC/1 mA [H_F]
< 5 x 10⁻⁶ (i.e. 1 failure in 5 x 10⁶ operations) Fault
probability

Max. short-circuit protective device
Fuseless
PKZMD-10/FAZ-B6/1 Type

Max. short-circuit protective device
Fuse [gG/gL]
10 A

Switching capacity

Rated operational current [I_e]
AC-15
115 V [I_e]
6 A

Rated operational current [I_e]
AC-15
220 V 230 V 240 V [I_e]
6 A

Rated operational current [I_e]
AC-15
380 V 400 V 415 V [I_e]
4 A

Rated operational current [I_e]
AC-15
500 V [I_e]
2 A

Rated operational current [I_e]
DC-13
24 V [I_e]
3 A

Rated operational current [I_e]
DC-13
42 V [I_e]
1.7 A

Rated operational current [I_e]
DC-13
60 V [I_e]
1.2 A

Rated operational current [I_e]
DC-13
110 V [I_e]
0.6 A

Rated operational current [I_e]
DC-13
220 V [I_e]
0.3 A

Lifespan, electrical
AC-15
230 V/0.5 A [Operations]

1.6 x 10⁶

Lifespan, electrical
AC-15
230 V/1.0 A [Operations]
1 x 10⁶

Lifespan, electrical
AC-15
230 V/3.0 A [Operations]
0.7 x 10⁶

Lifespan, electrical
DV-13
12 V/2.8 A [Operations]
1.2 x 10⁶

Auxiliary contacts

Rated operational voltage [U_e]
Rated operational voltage [U_e]
500 V AC

Rated operational voltage [U_e]
Rated operational voltage, max. [U_e]
220 V DC

Conventional thermal current [I_{th} = I_e]
4 CSA

Rated operational current [I_e]
Different rated operational currents when
used as auxiliary contact for NZM circuit-breaker

				M22- (C)K10(01)	M22- CK11(02) (20)	XHV
		bei				
		AC =				
		50/60				
		Hz				
	Bemessungsbetriebsstrom					
AC-15	115 V	le	A	4	4	4
	230 V	le	A	4	4	4
	400 V	le	A	2	-	2
	500 V	le	A	1	-	1
DC-13	24 V	le	A	3	3	3
	42 V	le	A	1.7	1	1.5
	60 V	le	A	1.2	0.8	0.8

110 V	le	A	0.6	0.5	0.5
220 V	le	A	0.3	0.2	0.2

Short-circuit protection
max. fuse
10 A gG/gL

Short-circuit protection
Max. miniature circuit-breaker
FAZ-B6/B1 A

Operating times

Early-make time of the HIV compared to the main contacts during with make and break switching.

(switch times with manual operation):

NZM1, FN1, N(S)1: ca. 20 ms

NZM2, FN2, N(S)2: ca. 20 ms

NZM3, FN3, N(S)3: ca. 20 ms

NZM4, N(S)4: approx. 90 ms, the HIV switch early
Offswitching not forward.

Terminal capacities

Solid or flexible conductor, with ferrule

1 x (0,75 - 2,5)

2 x (0,75 - 2,5) mm²

UL/CSA

Rated operational current [I_e]

5 A – 600 V AC

1 A - 250 V DC A

Other technical data (sheet catalogue)

Maximum equipment and position of the internal accessories

DESIGN VERIFICATION AS PER IEC/EN 61439

Technical data for design verification

Rated operational current for specified heat
dissipation [I_n]
6 A

Heat dissipation per pole, current-dependent [P_{vid}]
0.11 W

Equipment heat dissipation, current-dependent
[P_{vid}]
0 W

Static heat dissipation, non-current-dependent [P_{vs}]
0 W

Heat dissipation capacity [P_{diss}]
0 W

Operating ambient temperature min.
-25 °C

Operating ambient temperature max.
+70 °C

IEC/EN 61439 design verification

10.2 Strength of materials and parts
10.2.2 Corrosion resistance
Meets the product standard's requirements.

10.2 Strength of materials and parts
10.2.3.1 Verification of thermal stability of
enclosures
Meets the product standard's requirements.

10.2 Strength of materials and parts
10.2.3.2 Verification of resistance of insulating
materials to normal heat
Meets the product standard's requirements.

10.2 Strength of materials and parts
10.2.3.3 Verification of resistance of insulating
materials to abnormal heat and fire due to internal
electric effects
Meets the product standard's requirements.

10.2 Strength of materials and parts
10.2.4 Resistance to ultra-violet (UV) radiation
Meets the product standard's requirements.

10.2 Strength of materials and parts
10.2.5 Lifting
Does not apply, since the entire switchgear needs to be evaluated.

10.2 Strength of materials and parts
10.2.6 Mechanical impact
Does not apply, since the entire switchgear needs to be evaluated.

10.2 Strength of materials and parts
10.2.7 Inscriptions
Meets the product standard's requirements.

10.3 Degree of protection of ASSEMBLIES
Does not apply, since the entire switchgear needs to be evaluated.

10.4 Clearances and creepage distances
Meets the product standard's requirements.

10.5 Protection against electric shock
Does not apply, since the entire switchgear needs to be evaluated.

10.6 Incorporation of switching devices and components
Does not apply, since the entire switchgear needs to be evaluated.

10.7 Internal electrical circuits and connections
Is the panel builder's responsibility.

10.8 Connections for external conductors
Is the panel builder's responsibility.

10.9 Insulation properties
10.9.2 Power-frequency electric strength
Is the panel builder's responsibility.

10.9 Insulation properties
10.9.3 Impulse withstand voltage
Is the panel builder's responsibility.

10.9 Insulation properties
10.9.4 Testing of enclosures made of insulating material
Is the panel builder's responsibility.

10.10 Temperature rise
The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.

10.11 Short-circuit rating
Is the panel builder's responsibility. The specifications for the switchgear must be observed.

10.12 Electromagnetic compatibility
Is the panel builder's responsibility. The specifications for the switchgear must be observed.

10.13 Mechanical function
The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

TECHNICAL DATA ETIM 7.0

Low-voltage industrial components (EG000017) / Auxiliary contact block (EC000041)

Electric engineering, automation, process control engineering / Low-voltage switch technology / Component for low-voltage switching technology / Auxiliary switch block (ecl@ss10.0.1-27-37-13-02 [AKN342013])

Number of contacts as change-over contact
0

Number of contacts as normally open contact
1

Number of contacts as normally closed contact
0

Number of fault-signal switches
0

Rated operation current I_e at AC-15, 230 V
6 A

Type of electric connection
Screw connection

Model
Top mounting and integrable

Mounting method
Front fastening

Lamp holder
None

APPROVALS

Product Standards
IEC/EN 60947-5; UL 508; CSA-C22.2 No. 14-05;
CSA-C22.2 No. 94-91; CE marking

UL File No.
E29184

UL Category Control No.
NKCR

CSA File No.
012528

CSA Class No.
3211-03

North America Certification
UL listed, CSA certified

Degree of Protection
UL/CSA Type: -

DIMENSIONS



A = 37.2



Pushbutton with M22-(C)K...
Pushbutton with M22-(C) LED... + M22-XLED...

