

Smoke Alarm

9V Battery Powered



& Wired Interconnection

Model Ei 605CRF Optical

- Supplied with Ei605MRF  module.
- Interconnect up to 12 battery powered alarms
- EN 14604:2005 3rd party approved
- Early detection to all standard domestic fires types
- Built-in high audibility warning sounder
- Large Easy to use Test/Hush button
- Hush Feature allows false alarm control
- Easy to install twist-on base design
- Aesthetically pleasing, compact design
- Innovative and robust optical chamber design
- Manufactured in Ireland to ISO 9001:2000
- 5 year Guarantee




Product Description

The Ei605CRF is an Optical Smoke Alarm using the light scatter principle, giving a quick response to all standard domestic fire types.

It's powered by a 9V replaceable alkaline battery (supplied with the alarm)

The Ei605CRF supports wired and wireless interconnection of up to 12 smoke alarms and 8 Remote Control devices.

A unique housecoding feature prevents the system from communicating with other nearby  systems.

Remote Control Switches (Ei411H) may be added to the system to provide remote Locate, Test and Hush functionality.

The Ei605CRF is designed for simple installation, commissioning and maintenance.

The Ei605CRF has a large, easy to use, combined Test/Hush button enables full testing of the alarm and the ability to silence false alarms.

Operation


- The smoke detector will activate the built in sounder upon sensing smoke particles.
- When configured as an interconnect system the alarm sensing the fire will also sound all the other smoke alarms.
- The red indicating LED will flash once every 40 seconds to show that the alarm is powered and it has performed an automatic self-test.
- The built in sounder will provide a minimum sound output of 85dB at 3m.
- Pressing and holding the "Test/Hush" button will perform a self test and sound the horn – checking the chamber, electronics and horn.
- Momentarily pressing the "Test/Hush" button when an alarm is sounding will set the alarm into "HUSH" mode. This reduces the sensitivity for a period of 10 minutes, after which the alarm automatically resets – providing control over false alarms.
- The alarm is not powered until it is connected to the twist on base, thus avoiding battery power consumption during storage and prior to installation.



Shannon Free Zone, Shannon, Co. Clare, Ireland.
Ph.+353 61 471277 Fax.+353 61 471053
Email. eielectronics@eilttd.ie
Web: www.eielectronics.com

Model Ei605CRF Optical

Technical Specification

Sensor:	Optical, uses light scatter from smoke particles	Alarm:	Piezoelectric-horn (built-in)
Sensitivity:	Complies with the requirements of BS EN 14604: 2005	Alarm Sound Output:	85dB (minimum) at 3m
Airspeed:	Essentially immune to the effect of airspeed.	Temperature Range:	0 to 40°C
Button Test:	Simulates the effect of smoke to check chamber, electronics and horn.	Humidity Range:	15% to 95% Relative Humidity – non condensing
Hush:	Silences nuisance alarm. Automatically resets after approximately 10 minutes.	Interconnect:	Hardwire interconnect up to 12 battery powered alarms. Up to 12 smoke alarms maybe  interconnected. In addition up to 8 Remote Control devices may be fitted
Supply Voltage:	9V Battery	Fixing:	Screw fixings supplied
Power-On Indicator:	Red LED flashes through cover every 40 seconds	Dimensions:	115mm (diameter) x 45mm (height)
		Weight:	200 grams
		Warranty:	5 year (limited) warranty
		Approvals:	VdS approved to BS EN14604:2005, CE approved, Manufactured to ISO 9001:2000 quality standards.

Installation & Placement

Specifications are subject to change



Alarms should be placed in accordance with the general guidelines shown in the diagram above. These recommendations are based on the problem of areas of “dead air” close to corners of rooms and apexes of ceilings, which could result in the prevention of smoke reaching the smoke detector

Please consult the Instruction Leaflet supplied with the Ei605CRF for detailed instructions as to how to correctly install and position the smoke detector

Important Precaution:

Do not install the actual smoke/heat alarm itself in new or renovated buildings until all work is completed (including floor coverings) and the building has been fully cleaned. (Excessive dust and debris from building work can contaminate the smoke chamber and cause problems, and it will also invalidate the guarantee). If it must be installed, cover it completely, particularly around the edges, with a dust cover (eg. a plastic bag), until all cleaning is finished.

Specifications are subject to change