



Farge: ■ lysegrå

Lik illustrasjon

Electrical data**Ratings per IEC/EN**

Nominell spenning (III/3)	800 V
Nominell strøm	17.5 A

Ex information

Nominell strlm (Ex e II)	16 A
--------------------------	------

Fysiske data

Bredde	7 mm / 0.276 tommer
Høyde	4,1 mm / 0.161 tommer
Dybde	19 mm / 0.748 tommer
Jumper-tilordning	1-2

Materielle data

Note (material data)

[Information on material specifications can be found here](#)

Farge	lysegrå
Isolasjonsmateriale	Polyamid (PA66)
Brannklasse UL94	V0
Brannbelastning	0.006 MJ
Vekt	0.7 g

Komersiell data

Product Group	22 (TOPJOB S)
eCl@ss 10.0	27-14-11-40
eCl@ss 9.0	27-14-11-40
ETIM 8.0	EC000489
ETIM 7.0	EC000489
PU (SPU)	25 Stk
Pakketype	bag
Opprinnelsesland	DE
GTIN	4055143698412
Tollsatsnummer	85366990990



Environmental Product Compliance	
RoHS Compliance Status	Compliant,No Exemption

Godkjenninger / sertifikater

Declarations of conformity and manufacturer's declarations



Godkjenning	Standard	Sertifikatnavn
Railway WAGO GmbH & Co. KG	-	Railway Ready

Nedlastinger

Environmental Product Compliance

Compliance Search

Environmental Product Compliance 2001-402

↓

Documentation				
Additional Information		Bid Text		
Technical Section	pdf 2240.62 KB	2001-402	19.02.2019	xml 2.51 KB
		2001-402	27.04.2017	doc 23.50 KB

CAD/CAE-Data	
CAD data	CAE data
2D/3D Models 2001-402	EPLAN Data Portal 2001-402
	WSCAD Universe 2001-402
	ZUKEN Portal 2001-402

Installasjonsmerknader

Sammenkobling



Insert push-in type jumper bar and push down until it hits backstop.




Removing a push-in type jumper bar:
Insert the operating tool between the jumper and partition wall of the dual jumper slots, then lift up the jumper. Place the operating tool in the center of jumpers for up to five contacts (see above), or alternately on both sides for jumpers with more than five contacts.

Sammenkobling



Custom jumpers are created by breaking and removing jumper contacts (2000, 2001, 2002, 2004 Series).




Marking with a felt-tip pen.


Sammenkobling




Stepping down via push-in type jumper bar.



Stepping down via push-in type jumper bar:
Commoning via closed terminal side with end plate allows jumpering over two cross-section sizes, e.g., from 16 mm² (6 AWG) to 6 mm² (10 AWG) or from 6 mm² (10 AWG) to 2.5 mm² (14 AWG) (see illustration above).



Stepping down via push-in type jumper bar:
Commoning via open terminal side with end plate allows jumpering over two cross-section sizes for 16 mm² (6 AWG) and 10 mm² (8 AWG) and one cross-section size for 6/4/2.5 mm² (10/12/14 AWG). An example: from 16 mm² (6 AWG) to 6 mm² (10 AWG) (see illustration above) or from 10 mm² (8 AWG) to 4 mm² (12 AWG).



Note:
The total current of the outgoing circuits must not exceed the nominal current of the step-down jumper/push-in type jumper bar.