



MIR LED

220-240V AC 50Hz CRI [Ra]:93 IP20

EN: SPECIFICATIONS Color temperature: Warm white. Beam angle: 120°. Class 1, 3000K Dimmable. Easy mounting. Easily connectable in chain.	NO: SPESIFIKASJONER Fargetemperatur: Varm hvit. Strålevinkel: 120°. Klasse 1, 3000K Dimmbar. Enkel montering. Enkel å seriekoble.	SE: SPECIFIKATIONER Färgtemperatur: Varmvit. Spridningsvinkel: 120°. Klass 1, 3000K Dimmbar. Enkel montering. Enkel att seriekoppla.
---	--	---

Length: 1200 mm 600 mm
1000 mm 300 mm

22mm 33mm

EN: Mir may be dimmed flicker-free to a low level with Phase-cut (GLI) dimmers, eg UniDim + 500IE (e.nr No: 14 059 03 Se: 13 602 40) or Mini impulsdimmer (No: 14 069 61 / Se: 13 602 82).

NO: Mir kan dimmes flimmerfritt helt ned med tilpasset fasesnitt (GLI) dimmer, f.eks UniDim+ 500IE (el.nr: 14 059 03) eller Mini impulsdimmer (14 069 61). Det kan også med fordel benyttes styringssystemer som f.eks X-Comfort.

SE: Mir dimbar flimmar ner med anpassad fassnitt (GLI) dimmer, t.ex. UniDim + 500IE (e.nr: 13 602 40) eller Mini impuls dimmer (e.nr: 13 602 82). Den kan också användas med fördel ledningssystem såsom X-Comfort.

EN:

Length: 1200 mm.	Length: 1000 mm.	Length: 600 mm.	Length: 300 mm.
LED power: 18W	LED power: 14W	LED power: 10W	LED power: 5W
LED QTY: 160 pcs	LED QTY: 130 pcs	LED QTY: 80 pcs	LED QTY: 40 pcs
Total Lumens: 1400 lm	Total Lumens: 1100 lm	Total Lumens: 700 lm	Total Lumens: 400 lm

NO:

Lengde: 1200 mm.	Lengde: 1000 mm.	Lengde: 600 mm.	Lengde: 300 mm.
LED styrke: 18W	LED styrke: 14W	LED styrke: 10W	LED styrke: 5W
LED antall: 160 stk	LED antall: 130 stk	LED antall: 80 stk	LED antall: 40 stk
Total Lumen: 1400 lm	Total Lumen: 1100 lm	Total Lumen: 700 lm	Total Lumen: 400 lm

SE:

Längd: 1200 mm.	Längd: 1000 mm.	Längd: 600 mm.	Längd: 300 mm.
LED styrka: 18W	LED styrka: 14W	LED styrka: 10W	LED styrka: 5W
Antal LED: 160 st	Antal LED: 130 st	Antal LED: 80 st	Antal LED: 40 st
Total Lumen: 1400 lm	Total Lumen: 1100 lm	Total Lumen: 700 lm	Total Lumen: 400 lm

EN: MOUNTING, NO: MONTERING, SE: MONTERING

1. EN: Shut of the main power before installation. Mark the fixture placement with a pencil and install mounting clips. NO: Koble fra strømmen ved montering. Marker armaturplasseringen med en blyant å fest monteringsklips.	SE: Stäng alltid av strömmen under montering. Markera armaturens placering med en penna och fäst monteringsklippet. 2. EN: Snap on the fixture. NO: Klikk på plass armaturet. SE: Tryck fast armaturen.	3. EN: Connect the power wire to power. NO: Koble kabler til strøm. SE: Anslut kablarna. 4. EN: Connect up to 15 pcs. fixtures. NO: Koble opp til 15 stk. armaturer. SE: Anslut upp till 15 st. armaturer.
---	---	--

EN: ACCESSORIES: 3306754 Mounting Clip for MIR. 3306755 Connector for MIR. 3306756 Straight connector 10 cm. for MIR. 3306757 Powercord 100 cm. for MIR. 3306763 MIR T piece. 3306764 MIR L (L) 3306765 MIR L (R) 3306766 MIR connection box.	NO: TILBEHØR: 3306754 Monteringsklips for MIR. 3306755 Skjøt for MIR. 3306756 Skjøt 10 cm. for MIR. 3306757 Tilkobling 100 cm. for MIR. 3306763 MIR T stykke. 3306764 MIR L (L) 3306765 MIR L (R) 3306766 MIR koblingsboks.	SE: TILBEHÖR: 3306754 Montering Clips för Mir. 3306755 Förlängning för MIR. 3306756 Förlängning 10 cm. för MIR. 3306757 Anslutning 100 cm. för MIR. 3306763 MIR T stycke. 3306764 MIR L (L) 3306765 MIR L (R) 3306766 MIR kopplingsdosa.
--	--	---