




Busbar terminal f. CU20x5(x10, x15)

Part no. K20X15/40-A
Catalog No. 012783

EL-Nummer 2459132
(Norway)

Delivery program

			
Product range			Ci insulated enclosures
Basic function			Prepared enclosures
Product function			Modular busbar system
Accessories			Terminal
Single unit/Complete unit			Modular system
Function			For fuse enclosures and busbar fuse enclosures as well as SE-RS-I43 busbar assemblies
For use with			CU20X5 CU20X10 CU20X15
Notes Terminal capacity for flat strip: from 3 x 9 x 0.8 mm Up to 10 x 16 x 0.8 mm Ø 4 - 10 mm ² (solid)			

Technical data ETIM 7.0

Low-voltage industrial components (EG000017) / Busbar terminal (EC000001)			
Electric engineering, automation, process control engineering / Electrical installation, device / Terminal (not overhead line) / Switch board (ecl@ss10.0.1-27-14-11-46 [BAA025013])			
Busbar thickness		mm	5 - 10
Busbar width		mm	20 - 20
Suitable for			Flat rail
Width clamp		mm	32
Max. conductor cross section		mm ²	124
Max. rated operation current I _e		A	400
Suitable for round conductor connection			Yes
Suitable for sector conductor connection			No
Suitable for strip conductor connection			Yes

Additional product information (links)

allowInterrupt=1&RevisionSelectionMethod=LatestReleased&noSaveAs=0&Render=1 model certification xEnergy Safety Ci	http://www.eaton.eu/DE/ecm/idcplg?IdcService=GET_FILE&noSaveAs=0&Render=1
allowInterrupt=1&RevisionSelectionMethod=LatestReleased&noSaveAs=0&Render=1 Save time – we assist you with expert pre-assembly	http://www.eaton.eu/DE/ecm/idcplg?IdcService=GET_FILE&noSaveAs=0&Render=1
allowInterrupt=1&RevisionSelectionMethod=LatestReleased&noSaveAs=0&Render=1 product information xEnergy Safety Ci	http://www.eaton.eu/DE/ecm/idcplg?IdcService=GET_FILE&noSaveAs=0&Render=1
tool for calculating the power loss for switching device combinations	http://www.eaton.eu/DE/Europe/Electrical/CustomerSupport/ConfigurationTools/TCtool/index.htm
configurator - xEnergy family	http://www.eaton.eu/DE/Europe/Electrical/CustomerSupport/ConfigurationTools/xEnergyMainSupport/index.htm