DATASHEET - NZMN2-4-PX250/VAR-TZ-SVE



NZM2 PXR25 circuit breaker - integrated energy measurement class 1, 250A, 4p, variable, earth-fault protection and zone selectivity, plug-in technology



Part no. NZMN2-4-PX250/VAR-TZ-SVE

192087

EL Number 4363139

(Norway)

(Norway)	
General specifications	
Product name	Eaton Moeller series NZM molded case circuit breaker electronic
Part no.	NZMN2-4-PX250/VAR-TZ-SVE
EAN	4015081926381
Product Length/Depth	190 millimetre
Product height	160 millimetre
Product width	145 millimetre
Product weight Product weight	3 kilogram
Compliances	RoHS conform
Certifications	IEC IEC/EN 60947
Product Tradename	NZM
Product Type	Molded case circuit breaker
Product Sub Type	Electronic
Delivery program	
Application	Use in unearthed supply systems at 690 V
Туре	Circuit breaker
Circuit breaker frame type	NZM2
Accessories required	NZM2-4-XSVS
Number of poles	Four-pole
Amperage Rating	250 A
Release system	Electronic release
Features	Motor drive optional Protection unit
Special features	LSIG overload protection and delayed and non-delayed short-circuit protective device, earth-fault protection Class 1 energy measurement, r.m.s. value measurement, and "thermal memory" USB interface for configuration and test function with Power Xpert Protection Manager software Zone selectivity ZSI Interface module in equipment supplied. Optionally communication-capable with internal Modbus RTU module or CAM Maximum back-up fuse, if the expected short-circuit currents at the installation location exceed the switching capacity of the circuit breaker (Rated short-circuit breaking capacity Icn) Rated current = rated uninterrupted current: 250 A
Fechnical Data - Electrical	
Voltage rating	690 V - 690 V
Rated insulation voltage (Ui)	690 V AC
Rated impulse withstand voltage (Uimp) at auxiliary contacts	6000 V
Rated impulse withstand voltage (Uimp) at main contacts	8000 V
Current rating of neutral conductor	0 - 60% - 100% of phase conductor
Rated short-time withstand current (t = 0.3 s)	1.9 kA
Rated short-time withstand current (t = 1 s)	1.9 kA
Earth-fault current setting (Ig) - min	50 x In 250 x In
Earth-fault current setting (Ig) - max Instantaneous current setting (Ii) - min	
	2 A
• · ·	12 A
Instantaneous current setting (li) - max	12 A
• · ·	12 A 100 A 250 A

Short delay current setting (Isd) - max	10 A
Short-circuit release delayed setting - min	200 A
Short-circuit release delayed setting - max	2500 A
Short-circuit release non-delayed setting - min	500 A
Short-circuit release non-delayed setting - max	3000 A
Rated short-circuit breaking capacity Ics (IEC/EN 60947) at 230 V, 50/60 Hz	85 kA
Rated short-circuit breaking capacity Ics (IEC/EN 60947) at 400/415 V, 50/60 Hz	50 kA
Rated short-circuit breaking capacity Ics (IEC/EN 60947) at 440 V, 50/60 Hz	35 kA
Rated short-circuit breaking capacity Ics (IEC/EN 60947) at 525 V, 50/60 Hz	25 kA
Rated short-circuit breaking capacity Ics (IEC/EN 60947) at 690 V, 50/60 Hz	5 kA
Rated short-circuit making capacity Icm at 240 V, 50/60 Hz	187 kA
Rated short-circuit making capacity Icm at 400/415 V, 50/60 Hz	105 kA
Rated short-circuit making capacity Icm at 440 V, 50/60 Hz	74 kA
Rated short-circuit making capacity Icm at 525 V, 50/60 Hz	53 kA
Rated short-circuit making capacity Icm at 690 V, 50/60 Hz	40 kA
Short-circuit total breaktime	< 10 ms
Electrical connection type of main circuit	Other
Isolation	500 V AC (between auxiliary contacts and main contacts) 300 V AC (between the auxiliary contacts)
Number of operations per hour - max	120
Handle type	Rocker lever
Utilization category	A (IEC/EN 60947-2)
Overvoltage category	III
Pollution degree	3
Lifespan, electrical	10000 operations at 400 V AC-1 7500 operations at 690 V AC-1 10000 operations at 415 V AC-1
Direction of incoming supply	As required
Technical Data - Mechanical	
Mounting Method	Built-in device plug-in technique Plug-in unit
Degree of protection	IP20 IP20 (basic degree of protection, in the operating controls area)
Degree of protection (IP), front side	IP66 (with door coupling rotary handle) IP40 (with insulating surround)
Degree of protection (terminations)	IP10 (tunnel terminal) IP00 (terminations, phase isolator and strip terminal)
Protection against direct contact	Finger and back-of-hand proof to DIN EN 50274/VDE 0106 part 110
Shock resistance	20 g (half-sinusoidal shock 20 ms)
Number of auxiliary contacts (change-over contacts)	0
Number of auxiliary contacts (normally closed contacts)	0
Number of auxiliary contacts (normally open contacts)	0
Position of connection for main current circuit	Connection at separate chassis part
Climatic proofing	Damp heat, cyclic, to IEC 60068-2-30 Damp heat, constant, to IEC 60068-2-78
Special features	LSIG overload protection and delayed and non-delayed short-circuit protective device, earth-fault protection Class 1 energy measurement, r.m.s. value measurement, and "thermal memory" USB interface for configuration and test function with Power Xpert Protection Manager software Zone selectivity ZSI Interface module in equipment supplied. Optionally communication-capable with internal Modbus RTU module or CAM Maximum back-up fuse, if the expected short-circuit currents at the installation location exceed the switching capacity of the circuit breaker (Rated short-circuit breaking capacity Icn) Rated current = rated uninterrupted current: 250 A
Lifespan, mechanical	20000 operations
Technical Data - Mechanical - Terminals	
Standard terminals	Screw terminal
Optional terminals	Box terminal. Connection on rear. Tunnel terminal
Terminal capacity (control cable)	0.75 mm² - 1.5 mm² (2x) 0.75 mm² - 2.5 mm² (1x)

Terminal capacity (aluminum solid conductor/cable)	16 mm² (1x) at tunnel terminal
Terminal capacity (aluminum stranded conductor/cable)	25 mm² - 185 mm² (1x) at tunnel terminal
Terminal capacity (copper busbar)	M8 at rear-side screw connection Min. 16 mm x 5 mm direct at switch rear-side connection Max. 24 mm x 8 mm direct at switch rear-side connection
Terminal capacity (copper solid conductor/cable)	6 mm² - 16 mm² (2x) direct at switch rear-side connection 16 mm² (1x) at tunnel terminal 10 mm² - 16 mm² (1x) at box terminal 6 mm² - 16 mm² (2x) at box terminal 10 mm² - 16 mm² (1x) direct at switch rear-side connection
Terminal capacity (copper stranded conductor/cable)	25 mm² - 185 mm² (1x) at 1-hole tunnel terminal 25 mm² - 70 mm² (2x) direct at switch rear-side connection 25 mm² - 185 mm² (1x) at box terminal 25 mm² - 185 mm² (1x) direct at switch rear-side connection 25 mm² - 70 mm² (2x) at box terminal
Terminal capacity (copper strip)	Min. 2 segments of 9 mm x 0.8 mm at box terminal Max. 8 segments of 24 mm x 1 mm (2x) at box terminal Max. 10 segments of 24 mm x 0.8 mm at rear-side connection (punched) Min. 2 segements of 16 mm x 0.8 mm at rear-side connection (punched) Max. 10 segments of 16 mm x 0.8 mm at box terminal
Design verification as per IEC/EN 61439 - technical data	
Rated operational current for specified heat dissipation (In)	250 A
Equipment heat dissipation, current-dependent	51.56 W
Ambient operating temperature - min	-25 °C
Ambient operating temperature - max	70 °C
Ambient storage temperature - min	40 °C
Ambient storage temperature - max	70 °C
Design verification as per IEC/EN 61439	
10.2.2 Corrosion resistance	Meets the product standard's requirements.
10.2.3.1 Verification of thermal stability of enclosures	Meets the product standard's requirements.
10.2.3.2 Verification of resistance of insulating materials to normal heat	Meets the product standard's requirements.
10.2.3.3 Resist. of insul. mat. to abnormal heat/fire by internal elect. effects	Meets the product standard's requirements.
10.2.4 Resistance to ultra-violet (UV) radiation	Meets the product standard's requirements.
10.2.5 Lifting	Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 Mechanical impact	Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 Inscriptions	Meets the product standard's requirements.
10.3 Degree of protection of assemblies	Does not apply, since the entire switchgear needs to be evaluated.
10.4 Clearances and creepage distances	Meets the product standard's requirements.
10.5 Protection against electric shock	Does not apply, since the entire switchgear needs to be evaluated.
10.6 Incorporation of switching devices and components	Does not apply, since the entire switchgear needs to be evaluated.
10.7 Internal electrical circuits and connections	Is the panel builder's responsibility.
10.8 Connections for external conductors	Is the panel builder's responsibility.
10.9.2 Power-frequency electric strength	Is the panel builder's responsibility.
10.9.3 Impulse withstand voltage	Is the panel builder's responsibility.
10.9.4 Testing of enclosures made of insulating material	Is the panel builder's responsibility.
10.10 Temperature rise	The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 Short-circuit rating	Is the panel builder's responsibility. The specifications for the switchgear must b observed.
10.12 Electromagnetic compatibility	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.13 Mechanical function	The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.
Additional information	
Functions	Earth-fault protection Systems, cable, selectivity and generator protection Integrated earth fault protection Zone selectivity

Technical data ETIM 9.0

Low-voltage industrial components (EG000017) / Power circuit-breaker for trafo/generator/installation protection (EC000228)

Electric engineering, automation, process control engineering / Low-voltage switch technology / Circuit breaker (LV < 1 kV) / Circuit breaker for power transformer, generator and system protection (ecl@ss13-27-37-04-09 [AJZ716018])

Protection (ecl@ss13-27-37-04-09 [AJZ/16018])

Rated permanent current lu

A 250

Rated short-oricuit breaking capacity lou at 400 V.50 Hz Overload release current setting Al 100 - 250 Al 100 - 250 Al 100 - 250 Al 2 - 10 Al 2 - 12 Power loss Al 2 - 12 Power loss Device construction Integrated earth fault protection Integrated earth fault protection Integrated earth fault protection of main circuit Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally open contact Number of auxiliary contacts as normally open contact With switched-off indicator With switched-off indicator With switched-off indicator With integrated under voltage release No Number of poles Position of connection for main current circuit Type of control element Complete device with protection unit Motor drive optional Motor drive optional Motor drive optional			
Overload release current setting A 100 - 250 Adjustment range short-term delayed short-circuit release A 2 - 10 Adjustment range undelayed short-circuit release A 2 - 12 Power loss W 51.56 Device construction William in device plug-in technique Integrated earth fault protection Yes Type of electrical connection of main circuit Other Suitable for DIN rail (top hat rail) mounting No Number of auxiliary contacts as normally closed contact No Number of auxiliary contacts as normally open contact 0 With switched-off indicator No With integrated under voltage release No Number of poles 4 Position of connection for main current circuit No Type of control element Connection at separate chassis part Complete device with protection unit Yes Motor drive integrated No Motor drive optional Yes	Rated voltage	V	/ 690 - 690
Adjustment range short-term delayed short-circuit release A 2 - 10 Adjustment range undelayed short-circuit release A 2 - 12 Power loss Built-in device plug-in technique Device construction Built-in device plug-in technique Integrated earth fault protection Yes Type of electrical connection of main circuit Other Suitable for DIN rail (top hat rail) mounting No DIN rail (top hat rail) mounting optional No Number of auxiliary contacts as normally closed contact 0 Number of auxiliary contacts as change-over contact No With switched-off indicator No With integrated under voltage release No Number of poles 4 Position of connection for main current circuit Connection at separate chassis part Type of control element Rocker lever Complete device with protection unit Yes Motor drive integrated No Motor drive optional Yes	Rated short-circuit breaking capacity Icu at 400 V, 50 Hz	k.A	xA 50
Adjustment range undelayed short-circuit release Power loss Device construction Integrated earth fault protection Type of electrical connection of main circuit Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact With switched-off indicator With integrated under voltage release Number of poles Position of connection for main current circuit Type of control element Complete device plug-in technique Ves Other No No No No O O O O O O O O O O O O O	Overload release current setting	А	A 100 - 250
Power loss Device construction Device construction Integrated earth fault protection Type of electrical connection of main circuit Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Number of auxiliary contacts as change-over contact Number of paukiliary contacts as change-over contact Number of paukiliary contacts as change-over contact Number of control top findicator Number of poles No	Adjustment range short-term delayed short-circuit release	А	A 2 - 10
Device construction Integrated earth fault protection Type of electrical connection of main circuit Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional No Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Number of auxiliary contacts as change-over contact No With switched-off indicator With integrated under voltage release No Number of poles Position of connection for main current circuit Type of control element Complete device with protection unit Motor drive integrated Motor drive optional	Adjustment range undelayed short-circuit release	А	A 2 - 12
Integrated earth fault protection Type of electrical connection of main circuit Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional No No Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Number of auxiliary contacts as change-over contact With switched-off indicator No With integrated under voltage release No Number of poles Position of connection for main current circuit Type of control element Complete device with protection unit Motor drive integrated Motor drive optional Yes Other No Other No No Connection at separate chassis part Rocker lever No No Yes	Power loss	W	N 51.56
Type of electrical connection of main circuit Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact No With switched-off indicator No With integrated under voltage release No No No No No No Connection at separate chassis part Type of control element Complete device with protection unit Motor drive integrated Motor drive optional	Device construction		Built-in device plug-in technique
Suitable for DIN rail (top hat rail) mounting DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Number of poles No	Integrated earth fault protection		Yes
DIN rail (top hat rail) mounting optional Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Number of auxiliary contacts as change-over contact Number of auxiliary contacts as change-over contact No With switched-off indicator No With integrated under voltage release No No Number of poles A Position of connection for main current circuit Type of control element Complete device with protection unit Motor drive integrated Motor drive optional No Yes	Type of electrical connection of main circuit		Other
Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Number of auxiliary contacts as change-over contact No With switched-off indicator With integrated under voltage release No Number of poles Ves No Connection at separate chassis part Rocker lever Complete device with protection unit Wotor drive integrated No Motor drive optional No No Ves	Suitable for DIN rail (top hat rail) mounting		No
Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact No With switched-off indicator With integrated under voltage release No Number of poles A Position of connection for main current circuit Type of control element Complete device with protection unit Motor drive integrated Motor drive optional O O O O O O O O O O O O O	DIN rail (top hat rail) mounting optional		No
Number of auxiliary contacts as change-over contact With switched-off indicator No With integrated under voltage release No Number of poles Position of connection for main current circuit Type of control element Complete device with protection unit Motor drive integrated Motor drive optional O No No No No No No No No No	Number of auxiliary contacts as normally closed contact		0
With switched-off indicator With integrated under voltage release No Number of poles Position of connection for main current circuit Type of control element Complete device with protection unit Motor drive optional No No No No No No No No Yes	Number of auxiliary contacts as normally open contact		0
With integrated under voltage release No Number of poles 4 Position of connection for main current circuit Type of control element Complete device with protection unit Motor drive optional No No No No No No Yes	Number of auxiliary contacts as change-over contact		0
Number of poles 4 Position of connection for main current circuit Connection at separate chassis part Type of control element Complete device with protection unit Motor drive optional 4 Connection at separate chassis part Rocker lever 7 Yes No Yes	With switched-off indicator		No
Position of connection for main current circuit Type of control element Complete device with protection unit Motor drive optional Connection at separate chassis part Rocker lever Yes No Yes	With integrated under voltage release		No
Type of control element Complete device with protection unit Motor drive optional Rocker lever Yes No Yes	Number of poles		4
Complete device with protection unit Yes Motor drive integrated No Motor drive optional Yes	Position of connection for main current circuit		Connection at separate chassis part
Motor drive integrated No Motor drive optional Yes	Type of control element		Rocker lever
Motor drive optional Yes	Complete device with protection unit		Yes
	Motor drive integrated		No
Degree of protection (IP)	Motor drive optional		Yes
	Degree of protection (IP)		IP20