

Eaton EP-400025

Catalog Number: EP-400025

Eaton DA1 Variable frequency drive, 230 V AC, 3-phase, 10.5 A, 2.2 kW, IP66/NEMA 4X, Radio interference suppression filter, OLED display, UV resistant



Photo is representative

General specifications

Product Name Eaton DA1 Variable frequency drive
Catalog Number EP-400025

Model Code DA1-32011FB-B66O
EAN 4015082950071

Product Length/Depth 171.5 mm
Product Height 257 mm

Product Width 188 mm
Product Weight 3.5 kg

Certifications
CE
Certified by UL for use in Canada
CSA-C22.2 No. 14
CUL
EAC
IEC/EN 61800-3
IEC/EN61800-3
IEC/EN61800-5
RCM
RoHS, ISO 9001
Safety: EN 61800-5-1: 2003
Specification for general requirements:
IEC/EN 61800-2
UkrSEPRO
UL
UL 508C
UL Category Control No.: NMMS, NMMS7

Catalog Notes
The brake resistors are assigned based on the maximum rated power of the variable frequency drive. Additional brake resistors and designs (e.g. different duty cycles) are available upon request.

General

Cable length

100 m, screened, maximum permissible, Motor feeder
150 m, unscreened, maximum permissible, Motor feeder
200 m, screened, with motor choke, maximum permissible, Motor feeder
300 m, unscreened, with motor choke, maximum permissible, Motor feeder
C2 ≤ 5 m, Radio interference level, maximum motor cable length
C3 ≤ 25 m, Radio interference level, maximum motor cable length

Communication interface

CANopen®, built in
EtherCAT, optional
Ethernet IP, optional
Modbus RTU, built in
Modbus-TCP, optional
OP-Bus (RS485), built in
PROFIBUS, optional
PROFINET, optional
BACnet/IP, optional

Connection to SmartWire-DT

No

Degree of protection

IP66
NEMA 4X

Electromagnetic compatibility

1st and 2nd environments (according to EN 61800-3)

Fitted with:

PC connection
Control unit
Breaking resistance
Additional PCB protection
Brake chopper
IGBT inverter
Internal DC link
OLED display
Radio interference suppression filter

Frame size

FS2

Functions

Climatic environmental conditions

Altitude

Max. 1000 m
Above 1000 m with 1 % derating per 100 m
Max. 4000 m

Ambient operating temperature - min

-10 °C

Ambient operating temperature - max

40 °C

Ambient operating temperature at 150% overload - min

-10 °C

Ambient operating temperature at 150% overload - max

40 °C

Ambient storage temperature - min

-40 °C

Ambient storage temperature - max

60 °C

Climatic proofing

< 95 average relative humidity (RH), no condensation, no corrosion

Main circuit

Efficiency

95.9 % (η)

Heat dissipation at current/speed

74 W at 100% current and 0% speed
90 W at 100% current and 50% speed
112 W at 100% current and 90% speed
42 W at 50% current and 0% speed
62 W at 50% current and 50% speed
74 W at 50% current and 90% speed
51 W at 25% current and 50% speed
43 W at 25% current and 0% speed

Input current ILN at 150% overload

13.2 A

Leakage current at ground IPE - max

1.73 mA

Mains switch-on frequency

4-quadrant operation possible

Mounting position

Vertical

Product Category

Variable frequency drives

Protection

Finger and back-of-hand proof, Protection against direct contact (BGV A3, VBG4)

Protocol

CAN

EtherNet/IP

MODBUS

Other bus systems

PROFIBUS

PROFINET IO

TCP/IP

BACnet/IP

Safety function/level

STO (Safe Torque Off, SIL3, PLe Cat 3)

Suitable for

Branch circuits, (UL/CSA)

Radio interference class

C1: for conducted emissions only

Optional external radio interference suppression filter for longer motor cable lengths and for use in different EMC environments

C2, C3: depending on the motor cable length, the connected load, and ambient conditions.

Maximum of one time every 30 seconds

Mains voltage - min

180 V

Mains voltage - max

264 V

Operating mode

Optional: Vector control with feedback (CLV)

Sensorless vector control (SLV)

Speed control with slip compensation

U/f control

Output frequency - min

0 Hz

Output frequency - max

500 Hz

Output voltage (U₂)

240 V AC, 3-phase

230 V AC, 3-phase

Overload current I_L at 150% overload

15.75 A

Rated control supply voltage

10 V DC (U_s, max. 10 mA)

Rated frequency - min

48 Hz

Rated frequency - max

62 Hz

Rated operational power at 220/230 V, 50 Hz, 1-phase

2.2 kW

Rated operational voltage

230 V AC, 3-phase

240 V AC, 3-phase

Resolution

0.1 Hz (Frequency resolution, setpoint value)

Short-circuit protection rating

17.5 A, UL (Class CC or J), Safety device (fuse or miniature circuit-breaker), Power Wiring

Starting current - max

200 %, I_H, max. starting current (High Overload), for 4 seconds every 40 seconds, Power section

Supply frequency

50/60 Hz

Switching frequency

16 kHz, 4 - 32 kHz adjustable (audible), fPWM, Power section, Main circuit

System configuration type

AC supply systems with earthed center point

Voltage rating - max

240 VAC

Motor rating

Assigned motor current I_M at 220 - 240 V, 60 Hz, 150% overload
9.6 A

Assigned motor current I_M at 230 V, 50 Hz, 150% overload
8.7 A

Assigned motor power at 230/240 V, 60 Hz, 1-phase
3 HP

Apparent power

Apparent power at 230 V
4.18 kVA

Apparent power at 240 V
4.36 kVA

Braking function

Braking resistance

35 Ω

Braking torque

Max. 30 % MN, Standard - Main circuit

Max. 100 % of rated operational current I_e , variable, DC - Main circuit

Max. 100 % of rated operational current I_e with external braking resistor - Main circuit

Switch-on threshold for the braking transistor

390 VDC

Control circuit

Number of inputs (analog)

2

Number of inputs (digital)

5

Number of outputs (analog)

2

Number of outputs (digital)

2

Number of relay outputs

2 (parameterizable, 1 N/O and 1 changeover contact, 6 A (250 V, AC-1) / 5 A (30 V, DC-1))

Rated control voltage (U_c)

24 V DC (external, max. 100 mA)

Design verification

Equipment heat dissipation, current-dependent P_{vid}

90.2 W

Heat dissipation capacity P_{diss}

0 W

Resources

3D models

[eaton-EP-400017-3d-model.stp](#)

[eaton-EP-400017-drawing.dwg](#)

Application notes

Heat dissipation per pole, current-dependent P_{vid}

0 W

Static heat dissipation, non-current-dependent P_{vs}

0 W

10.2.2 Corrosion resistance

Meets the product standard's requirements.

10.2.3.1 Verification of thermal stability of enclosures

Meets the product standard's requirements.

10.2.3.2 Verification of resistance of insulating materials to normal heat

Meets the product standard's requirements.

10.2.3.3 Resist. of insul. mat. to abnormal heat/fire by internal elect. effects

Meets the product standard's requirements.

10.2.4 Resistance to ultra-violet (UV) radiation

Meets the product standard's requirements.

10.2.5 Lifting

Does not apply, since the entire switchgear needs to be evaluated.

10.2.6 Mechanical impact

Does not apply, since the entire switchgear needs to be evaluated.

10.2.7 Inscriptions

Meets the product standard's requirements.

10.3 Degree of protection of assemblies

Does not apply, since the entire switchgear needs to be evaluated.

10.4 Clearances and creepage distances

Meets the product standard's requirements.

10.6 Incorporation of switching devices and components

Does not apply, since the entire switchgear needs to be evaluated.

10.7 Internal electrical circuits and connections

Is the panel builder's responsibility.

10.8 Connections for external conductors

Is the panel builder's responsibility.

10.9.2 Power-frequency electric strength

Is the panel builder's responsibility.

10.9.3 Impulse withstand voltage

Start, Stopp und Betrieb

Master slave operation

Starting, Stopping and Operation

Operating Permanent Magnet and Brushless DC Motors

Motor data Motor Protection V/f curves for induction motors

I/O Configuration

The OP System Bus - Parameterizing - Control

Conformal Coating

Dependency of the output current on switching frequency and ambient temperature

DX-COM-STICK3_Connection

Hoist applications

Equal load sharing with the droop function

Electromagnetic compatibility (EMC)

How does the internal motor protection work?

Closed Loop Vector Control

Use of multiple ramps

PID controller

Access to Parameter Level 2 and 3 Parameter Lock RESET

Connecting drives to generator supplies

Update DX-COM-STICK3

Dual Rating What exactly does that mean?

Setpoint Setting

Vector Control of Induction Motors

Brochures

[eaton-powerxl-variable-frequency-drives-dc1-da1-brochure-br040001en-en-us.pdf](#)

Catalogues

Drives - Product range catalog

Product Range Catalog Drives Engineering

Declarations of conformity

[DA-DC-00005013.pdf](#)

[DA-DC-00005022.pdf](#)

Installation instructions

[eaton-da1-variable-frequency-drive-il040061zu.pdf](#)

Installation videos

PowerXL Variable Frequency Drives DC1 and DA1 - EN

Video PowerXL DA1

Manuals and user guides

Is the panel builder's responsibility.

10.9.4 Testing of enclosures made of insulating material

Is the panel builder's responsibility.

10.10 Temperature rise

The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.

10.11 Short-circuit rating

Is the panel builder's responsibility. The specifications for the switchgear must be observed.

10.12 Electromagnetic compatibility

Is the panel builder's responsibility. The specifications for the switchgear must be observed.

10.13 Mechanical function

The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

[eaton-da1-variable-frequency-drive-mn040063-en-us.pdf](#)

mCAD model

[eaton-cadenas-front_view-p2_ip66_size2_non_switched_front.pra](#)

[eaton-cadenas-side_view-p2_ip66_size2_non_switched_side.pra](#)

[eaton-cadenas-path-drives-p2_ip66_size2_non_switched.3db](#)

Multimedia

System solutions based on EtherCAT

Looking for variable frequency drives DC1 and DA1 which can be used in harsh environments?

Software, firmware, and applications

[eaton-powerxl-da1-ethercat-esi-for-omron-v311.zip](#)

[eaton-powerxl-da1-profinet-gsdml-v226.zip](#)

[eaton-powerxl-pcsoftware-drivesconnect-v1501.zip](#)

[eaton-powerxl-dx-comstick3-ble-drivers.zip](#)

[eaton-powerxl-da1-profinet-tia-v12-library.zip](#)

[eaton-powerxl-da1-profibusb-gsd-v216.zip](#)

[eaton-powerxl-dx-cbl-pc-3m0-usb-driver.zip](#)

[eaton-powerxl-da1-firmware-release-note-mz040041en-us.pdf](#)

[eaton-powerxl-da1-devicenet-eds-v100.zip](#)

[eaton-powerxl-da1-canopen-codesys-v3-library.zip](#)

[eaton-powerxl-dx-cbl-pc-1m5-usb-driver.zip](#)

[eaton-powerxl-da1-ethernetip-eds-v150.zip](#)

[eaton-powerxl-da1-ethercat-esi-v310.zip](#)

[eaton-powerxl-da1-swd-codesys-v3-library.zip](#)

[eaton-powerxl-da1-canopen-eds-v250.zip](#)