

Specifications



Photo is representative



Eaton EP-400022

Eaton DA1 Variable frequency drive, 230 V AC, 3-phase, 4.3 A, 0.75 kW, IP66/NEMA 4X, Radio interference suppression filter, OLED display, Local controls, UV resistant

General specifications

PRODUCT NAME Eaton DA1 Variable frequency drive

CATALOG NUMBER EP-400022

MODEL CODE DA1-324D3FB-B6SO

EAN 4015082950040

PRODUCT LENGTH/DEPTH 182 mm

PRODUCT HEIGHT 257 mm

PRODUCT WIDTH 188 mm

PRODUCT WEIGHT 3.5 kg

CE
Certified by UL for use in Canada
CSA-C22.2 No. 14
CUL
EAC
IEC/EN 61800-3
IEC/EN61800-3
IEC/EN61800-5
RCM
RoHS, ISO 9001
Safety: EN 61800-5-1: 2003

CERTIFICATIONS

Specification for general requirements: IEC/EN 61800-2
UkrSEPRO
UL
UL 508C
UL Category Control No.: NMMS, NMMS7
UL File No.: E172143
UL report applies to both US and Canada

CATALOG NOTES

The brake resistors are assigned based on the maximum rated power of the variable frequency drive. Additional brake

EATON

Powering Business Worldwide

resistors and designs (e.g. different duty cycles) are available upon request.

General

CABLE LENGTH	100 m, screened, maximum permissible, Motor feeder 150 m, unscreened, maximum permissible, Motor feeder 200 m, screened, with motor choke, maximum permissible, Motor feeder 300 m, unscreened, with motor choke, maximum permissible, Motor feeder C2 ≤ 5 m, Radio interference level, maximum motor cable length C3 ≤ 25 m, Radio interference level, maximum motor cable length
COMMUNICATION INTERFACE	CANopen®, built in EtherCAT, optional Ethernet IP, optional Modbus RTU, built in Modbus-TCP, optional OP-Bus (RS485), built in PROFIBUS, optional PROFINET, optional BACnet/IP, optional
CONNECTION TO SMARTWIRE-DT	No
DEGREE OF PROTECTION	IP66 NEMA 4X
ELECTROMAGNETIC COMPATIBILITY	1st and 2nd environments (according to EN 61800-3)
FITTED WITH:	PC connection Control unit Breaking resistance Additional PCB protection Brake chopper IGBT inverter Internal DC link OLED display Radio interference suppression filter Local controls
FRAME SIZE	FS2
FUNCTIONS	4-quadrant operation possible
MOUNTING POSITION	Vertical
PRODUCT CATEGORY	Variable frequency drives
PROTECTION	Finger and back-of-hand proof, Protection against direct contact (BGV A3,

Climatic environmental conditions

ALTITUDE	Max. 1000 m Above 1000 m with 1 % derating per 100 m Max. 4000 m
AMBIENT OPERATING TEMPERATURE - MIN	-10 °C
AMBIENT OPERATING TEMPERATURE - MAX	40 °C
AMBIENT OPERATING TEMPERATURE AT 150% OVERLOAD - MIN	-10 °C
AMBIENT OPERATING TEMPERATURE AT 150% OVERLOAD - MAX	40 °C
AMBIENT STORAGE TEMPERATURE - MIN	-40 °C
AMBIENT STORAGE TEMPERATURE - MAX	60 °C
CLIMATIC PROOFING	< 95 average relative humidity (RH), no condensation, no corrosion

	VBG4)
PROTOCOL	CAN EtherNet/IP MODBUS Other bus systems PROFIBUS PROFINET IO TCP/IP BACnet/IP
SAFETY FUNCTION/LEVEL	STO (Safe Torque Off, SIL3, PLe Cat 3)
SUITABLE FOR	Branch circuits, (UL/CSA)
RADIO INTERFERENCE CLASS	C1: for conducted emissions only Optional external radio interference suppression filter for longer motor cable lengths and for use in different EMC environments C2, C3: depending on the motor cable length, the connected load, and ambient conditions.

Main circuit

EFFICIENCY	94.7 % (η)
HEAT DISSIPATION AT CURRENT/SPEED	51 W at 100% current and 0% speed 50 W at 100% current and 50% speed 59 W at 100% current and 90% speed 36 W at 50% current and 0% speed 40 W at 50% current and 50% speed 42 W at 50% current and 90% speed 33 W at 25% current and 50% speed 32 W at 25% current and 0% speed
INPUT CURRENT I_{LN} AT 150% OVERLOAD	5.7 A
LEAKAGE CURRENT AT GROUND I_{PE} - MAX	1.73 mA
MAINS SWITCH-ON FREQUENCY	Maximum of one time every 30 seconds
MAINS VOLTAGE - MIN	180 V
MAINS VOLTAGE - MAX	264 V
OPERATING MODE	Optional: Vector control with feedback (CLV) Sensorless vector control (SLV) Speed control with slip compensation U/f control
OUTPUT FREQUENCY - MIN	0 Hz
OUTPUT FREQUENCY - MAX	500 Hz
OUTPUT VOLTAGE (U₂)	230 V AC, 3-phase 240 V AC, 3-phase
OVERLOAD CURRENT I_L AT 150% OVERLOAD	6.45 A
RATED CONTROL SUPPLY VOLTAGE	10 V DC (U _s , max. 10 mA)
RATED FREQUENCY - MIN	48 Hz
RATED FREQUENCY - MAX	62 Hz
RATED OPERATIONAL POWER AT 220/230 V, 50 HZ, 1-PHASE	0.75 kW
RATED OPERATIONAL VOLTAGE	240 V AC, 3-phase 230 V AC, 3-phase
RESOLUTION	0.1 Hz (Frequency)

Motor rating

ASSIGNED MOTOR CURRENT I_M AT 220 - 240 V, 60 HZ, 150% OVERLOAD	4.2 A
ASSIGNED MOTOR CURRENT I_M AT 230 V, 50 HZ, 150% OVERLOAD	3.2 A
ASSIGNED MOTOR POWER AT 230/240 V, 60 HZ, 1-PHASE	1 HP

	resolution, setpoint value)
SHORT-CIRCUIT PROTECTION RATING	10 A, UL (Class CC or J), Safety device (fuse or miniature circuit-breaker), Power Wiring
STARTING CURRENT - MAX	200 %, IH, max. starting current (High Overload), for 4 seconds every 40 seconds, Power section
SUPPLY FREQUENCY	50/60 Hz
SWITCHING FREQUENCY	16 kHz, 4 - 32 kHz adjustable (audible), fPWM, Power section, Main circuit
SYSTEM CONFIGURATION TYPE	AC supply systems with earthed center point
VOLTAGE RATING - MAX	240 VAC

Apparent power

APPARENT POWER AT 230 V 1.71 kVA

APPARENT POWER AT 240 V 1.79 kVA

Control circuit

NUMBER OF INPUTS (ANALOG) 2

NUMBER OF INPUTS (DIGITAL) 5

NUMBER OF OUTPUTS (ANALOG) 2

NUMBER OF OUTPUTS (DIGITAL) 2

NUMBER OF RELAY OUTPUTS 2 (parameterizable, 1 N/O and 1 changeover contact, 6 A (250 V, AC-1) / 5 A (30 V, DC-1))

RATED CONTROL VOLTAGE (UC) 24 V DC (external, max. 100 mA)

Braking function

BRAKING RESISTANCE 100 Ω

BRAKING TORQUE Max. 30 % MN, Standard - Main circuit
Max. 100 % of rated operational current I_e , variable, DC - Main circuit
Max. 100 % of rated operational current I_e with external braking resistor - Main circuit

SWITCH-ON THRESHOLD FOR THE BRAKING TRANSISTOR 390 VDC

Design verification

EQUIPMENT HEAT DISSIPATION, CURRENT-DEPENDENT PVID 39.75 W

HEAT DISSIPATION CAPACITY PDISS 0 W

HEAT DISSIPATION PER POLE, CURRENT-DEPENDENT PVID 0 W

STATIC HEAT DISSIPATION, NON-CURRENT-DEPENDENT PVS 0 W

10.2.2 CORROSION RESISTANCE Meets the product standard's requirements.

10.2.3.1 VERIFICATION OF THERMAL STABILITY OF Meets the product standard's requirements.

ENCLOSURES	
10.2.3.2 VERIFICATION OF RESISTANCE OF INSULATING MATERIALS TO NORMAL HEAT	Meets the product standard's requirements.
10.2.3.3 RESIST. OF INSUL. MAT. TO ABNORMAL HEAT/FIRE BY INTERNAL ELECT. EFFECTS	Meets the product standard's requirements.
10.2.4 RESISTANCE TO ULTRA-VIOLET (UV) RADIATION	Meets the product standard's requirements.
10.2.5 LIFTING	Does not apply, since the entire switchgear needs to be evaluated.
10.2.6 MECHANICAL IMPACT	Does not apply, since the entire switchgear needs to be evaluated.
10.2.7 INSCRIPTIONS	Meets the product standard's requirements.
10.3 DEGREE OF PROTECTION OF ASSEMBLIES	Does not apply, since the entire switchgear needs to be evaluated.
10.4 CLEARANCES AND CREEPAGE DISTANCES	Meets the product standard's requirements.
10.6 INCORPORATION OF SWITCHING DEVICES AND COMPONENTS	Does not apply, since the entire switchgear needs to be evaluated.
10.7 INTERNAL ELECTRICAL CIRCUITS AND CONNECTIONS	Is the panel builder's responsibility.
10.8 CONNECTIONS FOR EXTERNAL CONDUCTORS	Is the panel builder's responsibility.
10.9.2 POWER-FREQUENCY ELECTRIC STRENGTH	Is the panel builder's responsibility.
10.9.3 IMPULSE WITHSTAND VOLTAGE	Is the panel builder's responsibility.
10.9.4 TESTING OF ENCLOSURES MADE OF INSULATING MATERIAL	Is the panel builder's responsibility.
10.10 TEMPERATURE RISE	The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
10.11 SHORT-CIRCUIT RATING	Is the panel builder's responsibility. The specifications for the switchgear must be observed.

**10.12 ELECTROMAGNETIC
COMPATIBILITY**

Is the panel builder's responsibility. The specifications for the switchgear must be observed.

**10.13 MECHANICAL
FUNCTION**

The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

Resources

3D MODELS

[eaton-EP-400016-drawing.dwg](#)

[eaton-EP-400016-3d-model.stp](#)

APPLICATION NOTES

[eaton-powerxl-da1-pid-controller-ap040025-en-us.pdf](#)

[eaton-powerxl-da1-pointer-to-parameter-ap040133-en-us.pdf](#)

[eaton-powerxl-da1-use-of-multiple-ramps-ap040031-en-us.pdf](#)

[Start, Stopp und Betrieb](#)

[eaton-powerxl-da1-droop-function-ap040023-en-us.pdf](#)

[eaton-powerxl-da1-starting-stopping-operation-ap040030-en-us.pdf](#)

[eaton-powerxl-da1-set-point-setting-ap040040-en-us.pdf](#)

[eaton-powerxl-da1-dc1-de1-system-bus-ap040022-en-us.pdf](#)

[eaton-powerxl-da1-dc1-db1-de1-rapidlink5-firmware-update-ap040214-en-us.pdf](#)

[eaton-powerxl-da1-dc1-de1-internal-motor-protection-ap040016-en-us.pdf](#)

[eaton-powerxl-da1-dc1-de1-conformal-coating-ap040182-en-us.pdf](#)

[eaton-powerxl-da1-i-o-configuration-ap040034-en-us.pdf](#)

[eaton-powerxl-vfd-dual-rating-ap040114-en-us.pdf](#)

[eaton-powerxl-da1-vector-control-induction-motors-ap040028-en-us.pdf](#)

	eaton-powerxl-da1-operating-pm-bldc-motors-ap040051-en-us.pdf eaton-powerxl-da1-master-slave-operation-ap040026-en-us.pdf eaton-powerxl-da1-hoist-applications-ap040032-en-us.pdf eaton-powerxl-dx-com-stick-3-ap040190-en-us.pdf eaton-powerxl-da1-derating-ap040039-en-us.pdf eaton-powerxl-da1-motor-vf-curves-induction-motors-ap040018-en-us.pdf Electromagnetic compatibility (EMC)
BROCHURES	eaton-powerxl-variable-frequency-drives-dc1-da1-brochure-br040001en-en-us.pdf
CATALOGUES	Product Range Catalog Drives Engineering
DECLARATIONS OF CONFORMITY	eaton-variable-frequency-drive-declaration-of-conformity-uk251134en.pdf eaton-variable-frequency-drive-declaration-of-conformity-eu250651en.pdf
INSTALLATION INSTRUCTIONS	eaton-da1-variable-frequency-drive-il040061zu.pdf
INSTALLATION VIDEOS	Video PowerXL DA1 PowerXL Variable Frequency Drives DC1 and DA1 - EN
MANUALS AND USER GUIDES	eaton-da1-variable-frequency-drive-mn040063-en-us.pdf
MULTIMEDIA	System solutions based on EtherCAT

[Looking for variable frequency drives DC1 and DA1 which can be used in harsh environments?](#)

[eaton-powerxl-da1-ethercat-esi-for-omron-v311.zip](#)

[eaton-powerxl-pcsoftware-drivesconnect-v1501.zip](#)

[eaton-powerxl-da1-devicenet-eds-v100.zip](#)

[eaton-powerxl-da1-firmware-release-note-mz040041en-us.pdf](#)

[eaton-powerxl-da1-canopen-codesys-v3-library.zip](#)

[eaton-powerxl-da1-ethercat-esi-v310.zip](#)

[eaton-powerxl-da1-profinet-gsdml-v226.zip](#)

[eaton-powerxl-dx-cbl-pc-1m5-usb-driver.zip](#)

[eaton-powerxl-da1-ethernetip-eds-v150.zip](#)

[eaton-powerxl-da1-profibusb-gsd-v216.zip](#)

[eaton-powerxl-da1-profinet-tia-v12-library.zip](#)

[eaton-powerxl-dx-cbl-pc-3m0-usb-driver.zip](#)

[eaton-powerxl-da1-swd-codesys-v3-library.zip](#)

[eaton-powerxl-da1-canopen-eds-v250.zip](#)

[eaton-powerxl-dx-comstick3-ble-drivers.zip](#)

SOFTWARE, FIRMWARE,
AND APPLICATIONS

PROJECT NAME:

PROJECT NUMBER:

PREPARED BY:

DATE:



Eaton Corporation plc
Eaton House
30 Pembroke Road
Dublin 4, Ireland
Eaton.com

Follow us on social media to get the latest product and support information.



© 2025 Eaton. All Rights Reserved.