



Fuse disconnecter, 25A DC, 10x38 mm

Part no. FCFDC10DI-2-SOL
Article no. 137257

Similar to illustration

Delivery programme

Product range			Fuse disconnecter
Application field			Residential buildings Utility buildings Open areas
Description			String protection of the PV generator The trip indication signals the tripped fuse link: 50 - 400 V flashing, 400 - 1000 V continuous for cylindrical fuse links for photovoltaic application sealable
Connection			Without flashing function
Rated operational voltage	U_e	V	1000
Rated operational current 240 V	I_e	A	25
Size			10 x 38
Pole			2 pole

Technical data ETIM 6.0

Low-voltage industrial components (EG000017) / Fuse switch disconnecter (EC001040)			
Electric engineering, automation, process control engineering / Low-voltage switch technology / Off-load switch, circuit breaker, control switch / Fuse switch disconnecter (ecI@ss8.1-27-37-14-01 [AKF058010])			
Version as main switch			No
Version as safety switch			Yes
Max. rated operation voltage U_e AC		V	0
Rated permanent current I_u		A	25
Rated operation power at AC-23, 400 V		kW	0
Conditioned rated short-circuit current I_q		kA	10
Rated short-time withstand current I_{cw}		kA	0
Suitable for fuses			Shape C1-C3
Number of poles			2
With error protection			No
Type of electrical connection of main circuit			Screw connection
Suitable for ground mounting			No
Suitable for front mounting 4-hole			No
Suitable for busbar mounting			No
Type of control element			-
Position control element			Front side
Motor drive optional			No
Motor drive integrated			No
Version as emergency stop installation			No
Degree of protection (IP), front side			IP20