



The UT-2 operates as an electrical converter between RS232 and RS485 communication interfaces. It can be used for programming of single access controller or the whole network (subsystem) of access controllers connected RS485 bus. UT-2 device enables bidirectional data transmission between access control devices and management software installed at PC.

**Features:**

- power supply 10-15 VDC
- average current consumption 60 mA
- maximum current consumption 150 mA
- configuration and communication within RACS 4 access control system
- universal RS232-RS485 converter for general applications by third parties
- integration of RACS 4 system with INTEGRA alarm modules (SATEL)
- environmental conditions of operation:
  - temperature from 0°C to +55°C
  - humidity from 10% to 95%
- dimensions: 68.0 x 100.0 x 35.0 mm (height x width x thickness)
- weight: ≈80.0 g
- CE mark

Order guide	
<i>Item</i>	<i>Description</i>
<b>UT-2</b>	RS232-RS485 interface

**Legal Notice**

This document is not intended to be a technical specification of the product and has informative character only. The Manufactures of product reserves right to change its characteristic without notice. The product features listed in this document refer to the entire series and depends on particular product version, configuration and additional equipment.

RevB © 2017 ROGER sp. z o.o. sp. k. All rights reserved.

This document is a subject to the Terms of Use in their current version published at the [www.roger.pl](http://www.roger.pl)