



174617 NZM N2-A125-BT

Overview

Specifications

Resources







# **DELIVERY PROGRAM**

Delivery program

Technical data

Product range Orcuit-breaker

Design verification as

Protective function System and cable protection

per IEC/EN 61439

Standard/Approval

Technical data ETIM 7.0

Installation type Fixed

Characteristics

Release system

Thermomagnetic release

Dimensions

Construction size NZM2

Number of poles 3 pole

Standard equipment Box terminal

# **Switching capacity**

 $400/415 \ V \ 50 \ Hz \ [l_{cu}] \ 50 \ kA$ 

# Rated current = rated uninterrupted current $[I_n = I_u]$

Rated current = rated uninterrupted current [ $I_h = I_u$ ] 125 A

### **Setting range**

Overload trip
[I<sub>r</sub>]
100 - 125 A

# **TECHNICAL DATA**

#### **General**

Standards IEC/EN 60947

Protection against direct contact Finger and back of hand proof to VDE 0106 Part 100

Climatic proofing Damp heat, constant, to IEC 60068-2-78 Damp heat, cyclic, to IEC 60068-2-30

Ambient temperature Ambient temperature, storage - 40 - + 70 °C

Ambient temperature Operation -25 - +70 °C

Mechanical shock resistance (10 ms halfsinusoidal shock) according to IEC 60068-2-27 20 (half-sinusoidal shock 20 ms) g

Safe isolation to EN 61140 Between auxiliary contacts and main contacts 500 V AC

Safe isolation to EN 61140 between the auxiliary contacts 300 V AC

#### Mounting position

Vertical and 90° in all directions

With XFI earth-fault release:



- NZM1, N1, NZM2, N2: vertical and 90° in all directions

with plug-in unit

- NZM1, N1, NZM2, N2: vertical, 90° right/left

with withdrawable unit:

- NZM3, N3: vertical, 90° right/left
- NZM4, N4: vertical

with remote operator:

- NZM2, N(S)2, NZM3, N(S)3, NZM4, N(S)4: vertical and 90° in all directions

Direction of incoming supply as required

Degree of protection Device In the operating controls area: IP20 (basic degree of protection)

Degree of protection **Enclosures** With insulating surround: IP40 With door coupling rotary handle: IP66

Degree of protection Terminations Tunnel terminal: IP10 Phase isolator and strip terminal: IP00

Other technical data (sheet catalogue)
Weight
Temperature dependency, Derating
Effective power loss

#### **Circuit-breakers**

Rated current = rated uninterrupted current  $[I_n = I_u]$  125 A

Rated surge voltage invariability [ $U_{mp}$ ] Main contacts 8000 V

Rated surge voltage invariability [ $U_{mp}$ ] Auxiliary contacts  $6000\ V$ 

Rated operational voltage  $[U_e]$  690 V AC

Rated operational voltage  $[U_e]$  750 V DC

The following settings are required in order to ensure correct tripping:

The fast-response release will take longer to respond when used for DC applications. Because of this, the setting on the trip block inscription, which is specified for AC currents, must be set to a lower value for DC currents.

DC correction factor for instantaneous release response value:

o NZM1: 1.25 o NZM2: 1.35 o NZM3: 1.45

Example: NZM3 le = 500A. Desired DC tripping

current: 10 \* le = 5000A.

Calculation:

- Desired DC value / correction factor = AC setting on trip block
- 5000A / 1.45 = 3448 A  $\sim$  7 \* le = Value that needs to be set on the trip block

Permitted circuit configurations:

Overvoltage category/pollution degree 111/3 Rated insulation voltage [U<sub>i</sub>] 1000 V Use in unearthed supply systems □ 690 V **Switching capacity** Rated short-circuit making capacity [I<sub>cm</sub>] 240 V [l<sub>cm</sub>] 187 kA Rated short-circuit making capacity  $\left[I_{cm}\right]$ 400/415 V [I<sub>cm</sub>] 110 kA Rated short-circuit making capacity [I<sub>cm</sub>] 440 V 50/60 Hz [l<sub>cm</sub>] 77 kA Rated short-circuit making capacity [I<sub>cm</sub>] 525 V 50/60 Hz [l<sub>cm</sub>] 55 kA Rated short-circuit making capacity [I<sub>cm</sub>] 690 V 50/60 H[lc] 40 kA Rated short-circuit breaking capacity  $I_{cn}[I_{cn}]$ Icu to IEC/EN 60947 test cycle O-t-OO [Icu] 240 V 50/60 Hz [l<sub>cu</sub>] 85 kA Rated short-circuit breaking capacity  $l_{cn}\left[l_{cn}\right]$ Icu to IEC/EN 60947 test cycle O-t-OO [Icu] 400/415 V 50/60 Hz [l<sub>cu</sub>] 50 kA Rated short-circuit breaking capacity  $I_{cn}\left[I_{cn}\right]$ Icu to IEC/EN 60947 test cycle O-t-CO [Icu] 440 V 50/60 Hz [ $I_{cu}$ ] 35 kA Rated short-circuit breaking capacity  $I_{cn}[I_{cn}]$ 

lcu to IEO/EN 60947 test cycle O-t-CO [lcu] 525 V 50/60 Hz [lcu] 25 kA

Rated short-circuit breaking capacity  $l_{cn}$  [ $l_{cn}$ ] lcu to IEC/EN 60947 test cycle O-t-CO [lcu] 690 V 50/60 Hz [ $l_{cu}$ ] 20 kA

Rated short-circuit breaking capacity  $l_{cn}$  [ $l_{cn}$ ] lcu to IEC/EN 60947 test cycle O-t-CO [lcu] 500 V DC [ $l_{cu}$ ] 30 kA

Rated short-circuit breaking capacity  $l_{cn}$  [ $l_{cn}$ ] lcu to IEC/EN 60947 test cycle O-t-CO [lcu] 750 V DC [ $l_{cu}$ ] 30 kA

Rated short-circuit breaking capacity  $l_{cn}$  [ $l_{cn}$ ] lcs to IEC/EN 60947 test cycle O-t-CO-t-CO [lcs] 240 V 50/60 Hz [ $l_{cs}$ ] 85 kA

Rated short-circuit breaking capacity  $l_{cn}$  [ $l_{cn}$ ] lcs to IEC/EN 60947 test cycle O-t-OO-t-OO [lcs] 400/415 V 50/60 Hz [ $l_{cs}$ ] 50 kA

Rated short-circuit breaking capacity  $l_{cn}$  [ $l_{cn}$ ] lcs to IEC/EN 60947 test cycle O-t-CO-t-CO [lcs] 440 V 50/60 Hz [ $l_{cs}$ ] 35 kA

Rated short-circuit breaking capacity  $l_{cn}$  [ $l_{cn}$ ] lcs to IEC/EN 60947 test cycle O-t-CO-t-CO [lcs] 525 V 50/60 Hz [ $l_{cs}$ ] 25 kA

Rated short-circuit breaking capacity  $l_{cn}$  [ $l_{cn}$ ] lcs to IEC/EN 60947 test cycle O-t-CO-t-CO [lcs] 690 V 50/60 Hz [ $l_{cs}$ ] 5 kA

Rated short-circuit breaking capacity  $l_{cn}$  [ $l_{cn}$ ] lcs to IEC/EN 60947 test cycle O-t-CO-t-CO [lcs] 500 V DC [ $l_{cs}$ ] 7.5 kA

Rated short-circuit breaking capacity Icn [Icn]

lcs to IEC/EN 60947 test cycle O-t-CO-t-CO [lcs] 750 V DC [lcs] 7.5 kA

Rated short-circuit breaking capacity  $l_{cn}$  [ $l_{cn}$ ] Maximum back-up fuse, if the expected short-circuit currents at the installation location exceed the switching capacity of the circuit-breaker.

Rated short-time withstand current  $t = 0.3 \, s \, [l_{\text{cw}}]$  1.9 kA

Rated short-time withstand current  $t = 1 s [l_{cw}]$  1.9 kA

Utilization category to IEC/EN 60947-2 A

Lifespan, mechanical(of which max. 50 % trip by shunt/undervoltage release) [Operations] 20000

Lifespan, electrical AC-1 400 V 50/60 Hz [Operations] 10000

Lifespan, electrical AC-1 415 V 50/60 Hz [Operations] 10000

Lifespan, electrical AC-1 690 V 50/60 Hz [Operations] 7500

Lifespan, electrical AC--3 400 V 50/60 Hz [Operations] 6500

Lifespan, electrical AC--3 415 V 50/60 Hz [Operations] 6500 Lifespan, electrical AC--3 690 V 50/60 Hz [Operations] 5000

Lifespan, electrical Max. operating frequency 120 Ops/h

Total break time at short-circuit < 10 ms

### **Terminal capacity**

Standard equipment Box terminal

Optional accessories Screw terminal Tunnel terminal connection on rear

Round copper conductor Box terminal Solid 1 x (10 - 16) 2 x (6 - 16) mm<sup>2</sup>

Round copper conductor Box terminal Stranded 1 x (25 - 185) 2 x (25 - 70) mm<sup>2</sup>

Round copper conductor Tunnel terminal Solid 1 x 16 mm²

Round copper conductor Tunnel terminal Stranded 1-hole 1 x (25 - 185) mm<sup>2</sup>

Round copper conductor
Bolt terminal and rear-side connection
Direct on the switch
Solid
1 x (10 - 16)

Round copper conductor
Bolt terminal and rear-side connection
Direct on the switch
Stranded
1 x (25 - 185)
2 x (25 - 70) mm<sup>2</sup>

Al circular conductor Tunnel terminal Solid 1 x 16 mm<sup>2</sup>

Al circular conductor Tunnel terminal Stranded Stranded 1 x (25 - 185) mm²

Qu strip (number of segments x width x segment thickness)
Box terminal [min.]
2 x 9 x 0.8 mm

Ou strip (number of segments x width x segment thickness)
Box terminal [max.]
10 x 16 x 0.8
(2x) 8 x 15.5 x 0,8 mm

Ou strip (number of segments x width x segment thickness)

Bolt terminal and rear-side connection

Flat copper strip, with holes [min.]

2 x 16 x 0.8 mm

Ou strip (number of segments x width x segment thickness)

Bolt terminal and rear-side connection

Flat copper strip, with holes [max.]

10 x 24 x 0.8 mm

Copper busbar (width x thickness) [mm]
Bolt terminal and rear-side connection
Screw connection
M8

Copper busbar (width x thickness) [mm] Bolt terminal and rear-side connection Direct on the switch [min.] 16 x 5 mm Copper busbar (width x thickness) [mm] Bolt terminal and rear-side connection Direct on the switch [max.] 24 x 8 mm

Control cables 1 x (0.75 - 2.5) 2 x (0.75 - 1.5) mm<sup>2</sup>

# **DESIGN VERIFICATION AS PER IEC/EN 61439**

#### Technical data for design verification

Rated operational current for specified heat dissipation [ $I_{h}$ ] 125 A

Equipment heat dissipation, current-dependent  $[P_{id}]$  27.61 W

Operating ambient temperature min. -25  $^{\circ}\text{C}$ 

Operating ambient temperature max. +70 °C

### IEC/EN 61439 design verification

10.2 Strength of materials and parts10.2.2 Corrosion resistanceMeets the product standard's requirements.

10.2 Strength of materials and parts 10.2.3.1 Verification of thermal stability of enclosures Meets the product standard's requirements.

iveets the product standard's requirements

10.2 Strength of materials and parts 10.2.3.2 Verification of resistance of insulating materials to normal heat Weets the product standard's requirements. 10.2 Strength of materials and parts 10.2.3.3 Verification of resistance of insulating materials to abnormal heat and fire due to internal electric effects Weets the product standard's requirements.

10.2 Strength of materials and parts 10.2.4 Resistance to ultra-violet (UV) radiation Meets the product standard's requirements.

10.2 Strength of materials and parts10.2.5 LiftingDoes not apply, since the entire switchgear needs to be evaluated.

10.2 Strength of materials and parts10.2.6 Mechanical impactDoes not apply, since the entire switchgear needs to be evaluated.

10.2 Strength of materials and parts10.2.7 InscriptionsMeets the product standard's requirements.

10.3 Degree of protection of ASSEVBLIES
Does not apply, since the entire switchgear needs
to be evaluated.

10.4 Clearances and creepage distances Meets the product standard's requirements.

10.5 Protection against electric shock
Does not apply, since the entire switchgear needs
to be evaluated.

10.6 Incorporation of switching devices and components

Does not apply, since the entire switchgear needs to be evaluated.

10.7 Internal electrical circuits and connections Is the panel builder's responsibility.

10.8 Connections for external conductors Is the panel builder's responsibility.

10.9 Insulation properties 10.9.2 Pow er-frequency electric strength Is the panel builder's responsibility.

10.9 Insulation properties 10.9.3 Impulse withstand voltage Is the panel builder's responsibility.

10.9 Insulation properties10.9.4 Testing of enclosures made of insulating materialIs the panel builder's responsibility.

10.10 Temperature rise
The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.

10.11 Short-circuit rating Is the panel builder's responsibility. The specifications for the switchgear must be observed.

10.12 Electromagnetic compatibility Is the panel builder's responsibility. The specifications for the switchgear must be observed.

10.13 Mechanical function

The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

# **TECHNICAL DATA ETIM 7.0**

 $Low-voltage\ industrial\ components\ (EC000017)\ /\ Pow\ er\ circuit-breaker\ for\ trafo/generator/installation\ protection\ (EC000228)$ 

Bectric engineering, automation, process control engineering / Low-voltage switch technology / Orcuit breaker (LV < 1 kV) / Orcuit breaker for power transformer, generator and system protection (ecl@ss10.0.1-27-37-04-09 [AJZ716013])

Rated permanent current lu 125 A

Rated voltage 690 - 690 V

Rated short-circuit breaking capacity Icu at 400 V, 50 Hz 50 kA
Overload release current setting 100 - 125 A
Adjustment range short-term delayed short-circuit release 0 - 0 A
Adjustment range undelayed short-circuit release 750 - 1250 A
Integrated earth fault protection No
Type of electrical connection of main circuit Frame clamp
Device construction Built-in device fixed built-in technique
Suitable for DIN rail (top hat rail) mounting No
DIN rail (top hat rail) mounting optional Yes
Number of auxiliary contacts as normally closed contact 0
Number of auxiliary contacts as normally open contact 0
Number of auxiliary contacts as change-over contact 0
With switched-off indicator No

With under voltage release No	
Number of poles 3	
Position of connection for main current circuit Front side	
Type of control element Rocker lever	
Complete device with protection unit Yes	
Motor drive integrated No	
Motor drive optional Yes	
Degree of protection (IP) IP20	
CHARACTERISTICS	
Let-through current	
Let-through energy	
DIMENSIONS	
☐ Blow out area, minimum clearance to adjacent parts	

 $\hfill \square$  Mnimum clearance to adjacent parts







Imprint | Privacy Policy | Legal Disclaimer | Terms and Conditions © 2021 by Eaton Industries GmbH