

KONDENSATORER

Kondensatorer

Icar leverer kondensatorer for fasekompensering av lysarmaturer. Vanpee lagerfører alle varianter for lysarmaturer.



DATATABELL

El-nr	Type	Spenning/frekvens	Diameter mm	Lengde mm	Festemutter	Kapsling
35 321 79	2 µF	250 V / 50–60 Hz	30	53	M8	Plast
32 321 80	4 µF	250 V / 50–60 Hz	30	53	M8	Plast
35 321 81	4,5 µF	250 V / 50–60 Hz	30	53	M8	Plast
35 321 82	6 µF	250 V / 50–60 Hz	30	53	M8	Plast
35 321 83	8 µF	250 V / 50–60 Hz	30	69	M8	Plast
35 321 84	10 µF	250 V / 50–60 Hz	30	69	M8	Plast
35 321 85	12 µF	250 V / 50–60 Hz	30	93	M8	Plast
35 321 86	16 µF	250 V / 50–60 Hz	30	93	M8	Plast
35 321 87	20 µF	250 V / 50–60 Hz	35	93	M8	Plast
35 321 88	25 µF	250 V / 50–60 Hz	35	93	M8	Plast
35 321 96	35 µF	250 V / 50–60 Hz	40	93	M8	Plast
35 321 89	45 µF	250 V / 50–60 Hz	40	103	M8	Aluminium
35 321 90	60 µF	250 V / 50–60 Hz	45	128	M8	Aluminium
35 321 91	50 µF	400 V / 50–60 Hz	45	128	M8	Aluminium
35 321 92	60 µF	400 V / 50–60 Hz	55	128	M8	Aluminium
35 321 93	40 µF	400 V / 50–60 Hz	45	128	M8	Aluminium
35 321 94	0,033 µF	250 V / 50–60 Hz				Plast
35 321 95	0,1 µF	250 V / 50–60 Hz				Plast