

Select your language



- [German](#)
- [English](#)
- [Spanish](#)
- [French](#)
- [Dutch](#)
- [Italian](#)
- [Polish](#)
- [Czech](#)
- [Russian](#)
- [Norwegian Bokmål](#)

Worldwide English



MSFAD-25 - Adapter, 25 A, Pole 3, For use with MSC-D, 25 A



191097 MSFAD-25

[Overview](#) [Specifications](#) [Resources](#)



191097 MSFAD-25

Adapter, 25 A, Pole 3, For use with MSC-D, 25 A

Alternate Catalog No.

EL-Nummer (Norway)

MSFD-25

1666804

Adapter, Product range: Accessories, Busbar adapters, Approved to UL 508, For use with: MSC-D, 25 A, Rated operational voltage: $U_e=690\text{ V}$, Rated operational current: $I_e=25\text{ A}$, Terminal capacity: AWG 12, (4 mm²), Adapter width: 45 mm, Adapter length: 160 mm, DIN rail: 1

- [Delivery program](#)
- [Technical data ETIM 7.0](#)
- [Dimensions](#)


Delivery program

Product range
Accessories
Accessories
Busbar adapters
Approved to UL 508
Rated operational voltage [U_e]
690 V
Rated operational current [I_e]
25 A
Terminal capacity
AWG 12
(4 mm²)
Adapter width
45 mm
Adapter length
160 mm
DIN rail
1
Quantity
For use with
MSC-D, 25 A
Pole
3

Technical data ETIM 7.0

Low-voltage industrial components (EG000017) / Busbar adapter (EC001531)
 Electric engineering, automation, process control engineering / Low-voltage switch technology / Busbar trunking system (LV circuitry) / Busbar adapter (low-voltage switching technology) (ec1@ss10.0.1-27-37-03-04 [ACN951011])
 Mounting rail armament
 1 mounting rail
 Type of electric connection
 3 conductors AWG 12
 Rated current In
 25 A
 Min. busbar thickness
 2 mm
 Max. busbar thickness
 2 mm
 Width of the adapter
 45 mm
 Rail width
 24 mm
 Busbar distance
 60 mm

Dimensions



CAD data

- [Product-specific CAD data](#)
(Web)
- [3D Preview](#)
(Web)

DWG files

- [DA-CD-adapter_msfad_25](#)
File
(Web)

edz files

- [DA-CE-ETN.MSFAD-25](#)
File
(Web)

Step files

- [DA-CS-adapter_msfad_25](#)
File
(Web)

Additional product information


- [Motor starters and "Special Purpose Ratings" for the North American market](#)
(PDF)
- [Busbar Component Adapters for modern Industrial control panels](#)
(PDF)

Product photo




1210PIC-419
Photo

3D drawing

- 
[1210DRV-565](#)
Line drawing

Dimensions single product

- 
[1210DIM-84](#)
Line drawing

Instruction Leaflet

- [adapter \(IL015082ZU\)](#)
Asset
(PDF, multilingual)

Declaration of Conformity

EU

- [Motor Starter Feeder System\(DA-DC-00003917\)](#)
Asset
(PDF)

Download-Center

- [Download-Center \(this item\)](#)
Eaton EMEA Download-Center - download data for this item
- [Download-Center](#)
Eaton EMEA Download-Center

 [Generate data sheet in PDF format](#)

 [Generate data sheet in Excel format](#)

 [Write a comment](#)

[Imprint](#) [Privacy Policy](#) [Legal Disclaimer](#) [Terms and Conditions](#)

© 2021 by Eaton Industries GmbH

