



169004 S811+V65V3S

Overview

Specifications

Resources







DELIVERY PROGRAM

Delivery program

Description

Technical data

With internal bypass contacts

Design verification as

per IEC/EN 61439

Function

Soft starter for three-phase loads, with control unit and pump algorithm, for 690-V grids

Technical data ETIM 7.0

Mains supply voltage (50/60 Hz) [U_{LN}] 200 - 690 V AC

Approvals

Supply voltage [U_s] 24 V DC

Dimensions

Control voltage [U_C] 24 V DC

Assigned motor rating (Standard connection, In-Line)

at 400 V, 50 Hz [P] 315 kW at 690 V, 50 Hz [P] 630 kW

at 460 V, 60 Hz [P] 500 HP

Rated operational current

AC-53 [l_e] 650 A

Startup class CLASS 10 (star-delta replacement) CLASS 20 (heavy starting duty $3 \times l_e$ for 45 s) CLASS 30 ($6 \times l_e$ for 30 s)

Rated operational voltage [Ue]

200 V

230 V

400 V

480 V

600 V

690 V

Connection to SmartWire-DT no

Frame size

V

Ordering information
Terminal blocks for the terminals are required for frame sizes T, U, and V -> Accessories

TECHNICAL DATA

General

Standards IEC/EN 60947-4-2 UL 508 CSA22.2-14-1995 GB14048

Approvals CE
Approvals UL CSA C-Tick CCC
Climatic proofing Damp heat, constant, to IEC 60068-2-3 Damp heat, cyclic, to IEC 60068-2-10
Ambient temperature Operation [ϑ] -30 - +50 °C
Ambient temperature Storage [9] -50 - +70 °C
Altitude 0 - 2000 m, above that each 100 m 0.5% Derating m
Mounting position As required
Degree of protection Degree of Protection IP20 (terminals IP00)
Degree of protection Integrated Protection type IP40 can be achieved on all sides with covers SS-IP20-N.
Protection against direct contact Finger- and back-of-hand proof
Overvoltage category/pollution degree Il/3
Shock resistance 15 g
Radio interference level (IEC/EN 55011)

Weight 41.4 kg

Main conducting paths

Rated operating voltage $[U_e]$ 200 - 690 V AC

Supply frequency [f_{LN}] 50/60 Hz

Rated operational current [l_e] AC-53 [l_e] 650 A

Assigned motor rating (Standard connection, In-Line) at 230 V, 50 Hz [P] 200 kW

Assigned motor rating (Standard connection, In-Line) at 400 V, 50 Hz [P] 315 kW

Assigned motor rating (Standard connection, In-Line) at $500\,\mathrm{V}$, $50\,\mathrm{Hz}$ [P] $450\,\mathrm{kW}$

Assigned motor rating (Standard connection, In-Line) at $690\ V$, $50\ Hz\ [P]$ $630\ kW$

Assigned motor rating (Standard connection, In-Line) at 200 V, 60 Hz [P] $200\,\mathrm{HP}$

Assigned motor rating (Standard connection, In-Line) at 230 V, 60 Hz [P] 250 HP

Assigned motor rating (Standard connection, In-Line) at 460 V, 60 Hz [P] $500\,\mathrm{HP}$

Assigned motor rating (Standard connection, In-Line) at 600 V, 60 Hz [P] 600 HP

Assigned motor rating (Standard connection, In-Line) at 690 V, 60 Hz [P] 750 HP

Assigned motor rating (delta connection) at 690 V, 60 Hz [P] 1300 HP

Overload cycle to IEC/EN 60947-4-2 AC-53a 650 A: AC-53a: 4.0 - 32: 99 - 3

Overload cycle to IEC/EN 60947-4-2 Internal bypass contacts

Short-circuit rating
Type "1" coordination
NZMN4-ME875

Terminal capacities

Cable lengths Solid 2 x (120 - 240) 4 x (70 - 240) 6 x (120 - 240) mm²

Cable lengths
Rexible with ferrule
2 x (120 - 240)
4 x (70 - 240)
6 x (120 - 240) mm²

Stranded 2 x (120 - 240) 4 x (70 - 240) 6 x (120 - 240) mm²

Cable lengths
Solid or stranded
2 x (4 - 500 kcmil)
4 x (4 - 500 kcmil)
6 x (4 - 500 kcmil) AWG

Control cables Solid 1 x (2.5 - 4) 2 x (1.0 - 2.5) mm²

Control cables
Flexible with ferrule
1 x (2.5 - 4)
2 x (1.0 - 2.5) mm²

Control cables Stranded 1 x (2.5 - 4) 2 x (1.0 - 2.5) mm²

Control cables Solid or stranded 38 x (12 - 14) 2 x (12 - 14) AWG

Control cables Tightening torque 0.4 Nm

Control cables Screwdriver 0,6 x 3,5 mm

Control circuit

Digital inputs
Control voltage
DC-operated
24 V DC +10 %/- 10 % V DC

Digital inputs Current consumption 24 V External 24 V 150 mA Digital inputs

Ourrent consumption 24 V

External 24 V (no-load)

100 mA

Digital inputs
Pick-up voltage
DC-operated
21.6 - 26.4 V DC

Digital inputs Drop-out voltage [x U_s] DC operated Drop-out voltage, DC-operated, max. $3\ V\ DC$

Digital inputs Pck-up time DC operated 100 ms

Digital inputs Drop-out time DC operated 100 ms

Regulator supply Voltage [U $_{\rm s}$] 24 V DC +10 %/- 10 % V

Regulator supply Current consumption [l_e] 1400 mA

Regulator supply

Ourrent consumption at peak performance (close bypass) at 24 V DC [I_{Peak}]

10/150 A/ms

Regulator supply Notes External supply voltage

Analog inputs

Number of current inputs

Analog inputs

Current input 4 - 20 mA Relay outputs Number Relay outputs of which programmable $\,$ Relay outputs Voltage range 120 V AC/DC V AC Relay outputs AC-11 current range 3 A, AC-11 A Soft start function Ramp times Acceleration Ramp time, max. $360 \, s$ Ramp times Deceleration 0 - 120 s Start voltage (= turn-off voltage) Start voltage, max. 85 % Start pedestal Start voltage, max. 85 % Kickstart Voltage Kickstart voltage, max. 100 % Kickstart Duration

50 Hz

2000 ms

Kickstart Duration 50 Hz max.

Kickstart Duration 60 Hz Kickstart Duration 60 Hz max. 2000 ms
Fields of application Fields of application Soft starting of three-phase asynchronous motors
Fields of application 3-phase motors
Functions
Fast switching (semiconductor contactor) - (minimum ramp time 1s)
Soft start function
Reversing starter External solution required (reversing contactor)
Suppression of closing transients
Current limitation
Overload monitoring
Underload monitoring
Fault memory 10 Faults
Suppression of DC components for motors

Communication Interfaces Modbus RTU

DESIGN VERIFICATION AS PER IEC/EN 61439

Technical data for design verification

Rated operational current for specified heat dissipation [I_n] 650 A

Heat dissipation per pole, current-dependent $[P_{\text{id}}]$ 0 W

Equipment heat dissipation, current-dependent $[P_{\text{vid}}]$ 109 W

Static heat dissipation, non-current-dependent [$P_{\!\scriptscriptstyle (\!S\!)}$] 109 W

Heat dissipation capacity $[P_{\text{diss}}]$ 0 W

Operating ambient temperature min. -30 °C

Operating ambient temperature max. $+50 \, ^{\circ}\mathrm{C}$

IEC/EN 61439 design verification

10.2 Strength of materials and parts10.2.2 Corrosion resistanceMeets the product standard's requirements.

10.2 Strength of materials and parts 10.2.3.1 Verification of thermal stability of enclosures Meets the product standard's requirements. 10.2 Strength of materials and parts10.2.3.2 Verification of resistance of insulating materials to normal heatWeets the product standard's requirements.

10.2 Strength of materials and parts 10.2.3.3 Verification of resistance of insulating materials to abnormal heat and fire due to internal electric effects Meets the product standard's requirements.

10.2 Strength of materials and parts10.2.4 Resistance to ultra-violet (UV) radiationWeets the product standard's requirements.

10.2 Strength of materials and parts10.2.5 LiftingDoes not apply, since the entire switchgear needs to be evaluated.

10.2 Strength of materials and parts10.2.6 Mechanical impactDoes not apply, since the entire switchgear needs to be evaluated.

10.2 Strength of materials and parts10.2.7 InscriptionsMeets the product standard's requirements.

10.3 Degree of protection of ASSEVBLIES

Does not apply, since the entire switchgear needs
to be evaluated.

10.4 Clearances and creepage distances Meets the product standard's requirements.

10.5 Protection against electric shock
Does not apply, since the entire switchgear needs
to be evaluated.

10.6 Incorporation of switching devices and components

Does not apply, since the entire switchgear needs to be evaluated.

10.7 Internal electrical circuits and connections is the panel builder's responsibility.

10.8 Connections for external conductors Is the panel builder's responsibility.

10.9 Insulation properties 10.9.2 Power-frequency electric strength Is the panel builder's responsibility.

10.9 Insulation properties10.9.3 Impulse withstand voltageIs the panel builder's responsibility.

10.9 Insulation properties10.9.4 Testing of enclosures made of insulating materialIs the panel builder's responsibility.

10.10 Temperature rise
The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.

10.11 Short-circuit rating Is the panel builder's responsibility. The specifications for the switchgear must be observed.

10.12 Electromagnetic compatibility Is the panel builder's responsibility. The specifications for the switchgear must be observed.

10.13 Mechanical function

The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

TECHNICAL DATA ETIM 7.0

Low-voltage industrial components (EG000017) / Soft starter (EC000640)

Bectric engineering, automation, process control engineering / Low-voltage switch technology / Load breakout, motor breakout / Semiconductor motor controller or soft starter (ecl@ss10.0.1-27-37-09-07 [ACO300011])

Rated operation current le at 40 °C Tu 650 A
Rated operating voltage Ue 200 - 690 V
Rated power three-phase motor, inline, at 230 V 200 kW
Rated power three-phase motor, inline, at 400 V 315 kW
Rated power three-phase motor, inside delta, at 230 V 200 kW
Rated power three-phase motor, inside delta, at 400 V 630 kW
Function Single direction
Internal bypass Yes
With display Yes
Torque control No
Rated surrounding temperature without derating 50 °C
Rated control supply voltage Us at AC 50HZ 0 - 0 V
Rated control supply voltage Us at AC 60HZ 0 - 0 V
Rated control supply voltage Us at DC 24 - 24 V

Integrated motor overload protection Yes
Release class Adjustable
Degree of protection (IP) IP00
Degree of protection (NEVA) Other
APPROVALS
Product Standards IEC/EN 60947-4-2; UL 508; CE marking
UL File No. E202571
UL Category Control No. NVFT
North America Certification UL listed
Suitable for Branch Circuits, not as BCPD
Max. Voltage Rating 690 Vac
Degree of Protection IP20 w ith kit









Imprint $\,|\,$ Privacy Policy $\,|\,$ Legal Disclaimer $\,|\,$ Terms and Conditions $\,@$ 2020 by Eaton Industries GmbH