



191669 NZMH2-VX100-S1

Overview

Specifications

Resources







DELIVERY PROGRAM

Delivery program

Product range Circuit-breaker

Technical data

Protective function

Design verification as

per IEC/EN 61439

Systems, cable, selectivity and generator protection

Technical data ETIM 7.0

Standard/Approval

IEC

Characteristics

Installation type

Fixed

Dimensions

Release system Bectronic release

Construction size

NZM2

Description

Rms. value measurement and "thermal memory"

Adjustable time delay setting to overcome current peaks tr at 6 x lr also infinity (without overload releases)

Adjustable delay time tsd

Number of poles 3 pole

Standard equipment Screw connection

Rated current = rated uninterrupted current [$I_h = I_u$] 100 A

Switching capacity

 $1000~V~50/60~Hz~[l_{cu}]$ 10~kA

Setting range

Overload trip [I_r] 40 - 100 A

Short-circuit releases \downarrow [l_{rm}] Non-delayed \downarrow [$l_i = l_n x ...$] 2-18

Short-circuit releases $[l_{rm}]$ Delayed $[l_{sd} = l_r \times ...]$ 2-10

TECHNICAL DATA

Circuit-breakers

Rated surge voltage invariability [U_{mp}] Main contacts 8000 V

Rated surge voltage invariability $[U_{imp}]$ Auxiliary contacts 6000 V Rated operational voltage [Ue] 1000 V AC Rated current = rated uninterrupted current $[I_n = I_u]$ 100 A Overvoltage category/pollution degree Rated insulation voltage [U] 690 V Use in unearthed supply systems □ 690 V Utilization category Ambient temperature Ambient temperature, storage - 40 - + 70 °C Ambient temperature Operation -25 - +70 °C Rated short-circuit making capacity [I_{cm}] 240 V 50/60 Hz [l_{cm}] 330 kA 400/415 V 50/60 Hz [l_{cm}] 330 kA 440 V 50/60 Hz [l_{cm}] 286 kA 525 V 50/60 Hz [l_{cm}] 110 kA

690 V 50/60 H [lc] 40 kA

1000 V 50/60 Hz [lcm] 17 kA

Rated short-circuit breaking capacity I_{cn} [I_{cn}]

lcu to IEC/EN 60947 test cycle O-t-CO [lcu] 240 V 50/60 Hz [lcu] 150 kA

lcu to IEC/EN 60947 test cycle O-t-CO [lcu] 400/415 V 50 Hz [lcu] 150 kA

lcu to IEC/EN 60947 test cycle O-t-CO [lcu] 440 V 50/60 Hz [lcu] 130 kA

lcu to IEC/EN 60947 test cycle O-t-CO [lcu] 525 V 50/60 Hz [lcu] 50 kA

lcu to IEC/EN 60947 test cycle O-t-CO [lcu] 690 V 50/60 Hz [lcu] 20 kA

lcu to IEC/EN 60947 test cycle O-t-CO [lcu] 1000 V 50/60 Hz [lcu] 10 kA

lcs to IEO/EN 60947 test cycle O-t-CO-t-CO [lcs] 230 V 50/60 Hz [lcs] 150 kA

lcs to IEC/EN 60947 test cycle O-t-CO-t-CO [lcs] 400/415 V 50/60 Hz [lcs] $\,$ 150 kA $\,$

lcs to IEC/EN 60947 test cycle O-t-CO-t-CO [lcs] 440 V 50/60 Hz [lcs] 130 kA

lcs to IEC/EN 60947 test cycle O-t-CO-t-CO [lcs] 525 V 50/60 Hz [lcs]

lcs to IEO/EN 60947 test cycle O-t-CO-t-CO [lcs] 690 V 50/60 Hz [lcs] 5 kA

lcs to IEC/EN 60947 test cycle O-t-CO-t-CO [lcs] 1000 V AC [lcs] 3 kA

Rated short-time withstand current

 $t = 0.3 s [l_{cw}]$ 1.9 kA

 $t = 1 s [l_{cw}]$ 1.9 kA

Lifespan, mechanical [Operations] 20000

Max. operating frequency 120 Ops/h

Lifespan, mechanical: of which max. 50 % trip by shunt/undervoltage release

Lifespan, electrical

1000 V 50/60 Hz [Operations] 3000

Terminal capacity

Standard equipment Screw connection

Round copper conductor Box terminal Solid 1 x (10 - 16) 2 x (6 - 16) mm²

Round copper conductor

Box terminal Stranded 1 x (25 - 185) 2 x (25 - 70) mm²

Round copper conductor Tunnel terminal Solid 1 x 16 mm²

Round copper conductor Tunnel terminal Stranded Stranded 1 x (25 - 185) mm²

Round copper conductor
Bolt terminal and rear-side connection
Direct on the switch
Solid
1 x (10 - 16)
2 x (6 - 16) mm²

Round copper conductor
Bolt terminal and rear-side connection
Direct on the switch
Stranded
1 x (25 - 185)
2 x (25 - 70) mm²

Al conductors, Ou cable Tunnel terminal Solid 1 x 16 mm²

Al conductors, Ou cable Tunnel terminal Stranded Stranded 1 x (25 - 185) mm²

Ou strip (number of segments x width x segment thickness)

Box terminal [min.]

2 x 9 x 0.8 mm

Ou strip (number of segments x width x segment thickness)

Box terminal [max.]

10 x 16 x 0.8

(2x) 8 x 15.5 x 0,8 mm

Ou strip (number of segments x width x segment thickness)

Bolt terminal and rear-side connection

Flat copper strip, with holes [min.]

2 x 16 x 0.8 mm

Ou strip (number of segments x width x segment thickness)

Bolt terminal and rear-side connection

Flat copper strip, with holes [max.]

10 x 24 x 0.8 mm

Copper busbar (width x thickness) [mm] Bolt terminal and rear-side connection Screw connection M8

Copper busbar (width x thickness) [mm] Bolt terminal and rear-side connection Direct on the switch [min.] 16 x 5 mm

Copper busbar (width x thickness) [mm] Bolt terminal and rear-side connection Direct on the switch [max.] 24 x 8 mm

Control cables 1 x (0.75 - 2.5) 2 x (0.75 - 1.5) mm²

DESIGN VERIFICATION AS PER IEC/EN 61439

Technical data for design verification

Rated operational current for specified heat dissipation [I $_{n}$] 100 A

Equipment heat dissipation, current-dependent $[P_{\text{vid}}]$ 8.25 W

Operating ambient temperature min. -25 $^{\circ}\text{C}$

IEC/EN 61439 design verification

10.2 Strength of materials and parts10.2.2 Corrosion resistanceMeets the product standard's requirements.

10.2 Strength of materials and parts 10.2.3.1 Verification of thermal stability of enclosures Meets the product standard's requirements.

10.2 Strength of materials and parts10.2.3.2 Verification of resistance of insulating materials to normal heatMeets the product standard's requirements.

10.2 Strength of materials and parts
10.2.3.3 Verification of resistance of insulating
materials to abnormal heat and fire due to internal
electric effects
Weets the product standard's requirements.

10.2 Strength of materials and parts 10.2.4 Resistance to ultra-violet (UV) radiation Meets the product standard's requirements.

10.2 Strength of materials and parts10.2.5 LiftingDoes not apply, since the entire switchgear needs to be evaluated.

10.2 Strength of materials and parts10.2.6 Mechanical impactDoes not apply, since the entire switchgear needs to be evaluated.

10.2 Strength of materials and parts10.2.7 InscriptionsMeets the product standard's requirements.

10.3 Degree of protection of ASSEVBLIES Does not apply, since the entire switchgear needs to be evaluated.

10.4 Clearances and creepage distances

Meets the product standard's requirements.

10.5 Protection against electric shock
Does not apply, since the entire switchgear needs
to be evaluated.

10.6 Incorporation of switching devices and components

Does not apply, since the entire switchgear needs to be evaluated.

10.7 Internal electrical circuits and connections Is the panel builder's responsibility.

10.8 Connections for external conductors Is the panel builder's responsibility.

10.9 Insulation properties 10.9.2 Power-frequency electric strength Is the panel builder's responsibility.

10.9 Insulation properties 10.9.3 Impulse withstand voltage Is the panel builder's responsibility.

10.9 Insulation properties10.9.4 Testing of enclosures made of insulating materialIs the panel builder's responsibility.

10.10 Temperature rise
The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.

10.11 Short-circuit rating Is the panel builder's responsibility. The specifications for the switchgear must be observed.

10.12 Electromagnetic compatibility Is the panel builder's responsibility. The specifications for the switchgear must be observed.

10.13 Mechanical function

The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

TECHNICAL DATA ETIM 7.0

Low-voltage industrial components (EG000017) / Power circuit-breaker for trafo/generator/installation protection (EC000228)

Bectric engineering, automation, process control engineering / Low-voltage switch technology / Orcuit breaker (LV < 1 kV) / Orcuit breaker for power transformer, generator and system protection (ecl@ss10.0.1-27-37-04-09 [AJZ716013])

Rated permanent current lu 100 A

Rated voltage 1000 - 1000 V

Rated short-circuit breaking capacity lcu at 400 V, $50 \, \text{Hz}$ $150 \, \text{kA}$

Overload release current setting 40 - 100 A

Adjustment range short-term delayed short-circuit release 2 - 10 A

Adjustment range undelayed short-circuit release 2 - 18 A

Integrated earth fault protection

Type of electrical connection of main circuit Screw connection

Device construction
Built-in device fixed built-in technique

Suitable for DIN rail (top hat rail) mounting No

DIN rail (top hat rail) mounting optional Yes
Number of auxiliary contacts as normally closed contact 0
Number of auxiliary contacts as normally open contact 0
Number of auxiliary contacts as change-over contact 0
With switched-off indicator No
With under voltage release No
Number of poles 3
Position of connection for main current circuit Front side
Type of control element Rocker lever
Complete device with protection unit Yes
Motor drive integrated No
Motor drive optional Yes
Degree of protection (IP) IP20

CHARACTERISTICS

Characteristic curve
Let-through current
Characteristic curve
Let-through energy
DIMENSIONS
□ Blow out area, minimum clearance to adjacent parts □ Minimum clearance to adjacent parts







Imprint | Privacy Policy | Legal Disclaimer | Terms and Conditions © 2020 by Eaton Industries GmbH