SIEMENS

Data sheet

. .

6GK5108-2BD00-2AB2

SCALANCE XB108-2 unmanaged IE switch, 8x 10/100 Mbit/s Ports, 2x 100 Mbit/s multimode SC, for setting up small star and line topologies; LED diagnostics,IP20, redundant power supply, 24 V AC/DC Manual available as a download



product type designation	SCALANCE XB108-2
transfer rate	
transfer rate	10 Mbit/s, 100 Mbit/s
interfaces / for communication / integrated	
number of electrical connections	
 for network components or terminal equipment 	8; RJ45
number of 100 Mbit/s SC ports	
• for multimode	2
interfaces / other	
number of electrical connections	
• for power supply	1
supply voltage, current consumption, power loss	
product component / connection for redundant	Yes
voltage supply	
type of voltage / 1 / of the supply voltage	DC
 supply voltage / 1 / rated value 	24 V
 power loss [W] / 1 / rated value 	7.2 W
 supply voltage / 1 / rated value 	19.2 28.8 V

 consumed current / 1 / maximum 	0.3 A
 product component / 1 / fusing at power supply 	Yes
input	
type of voltage / 2 / of the supply voltage	
supply voltage / 2 / rated value	19.2 28.8 V
ambient conditions	
ambient temperature	
during operation	0 60 °C
during storage	-40 +80 °C
during transport	-40 +80 °C
relative humidity	
• at 25 °C / without condensation / during	95 %
operation / maximum	1000
protection class IP	IP20
design, dimensions and weights	
design	compact
width	80 mm
height	117 mm
depth	109 mm
net weight	0.34 kg
fastening method	
 35 mm top hat DIN rail mounting 	Yes
 wall mounting 	No
 S7-300 rail mounting 	No
 S7-1500 rail mounting 	No
product functions / management, configuration, eng	jineering
product function	
multiport mirroring	No
• CoS	Yes
PROFINET conformity class	A
product function / switch-managed	No
product functions / redundancy	
product function	
 Parallel Redundancy Protocol (PRP)/operation in the PRP-network 	Yes
 Parallel Redundancy Protocol (PRP)/Redundant Network Access (RNA) 	No
standards, specifications, approvals	
standard	
• for FM	FM3611: Class 1, Divison 2, Group A, B, C, D / T4, CL.1, Zone 2, GP. IIC, T4

 for hazardous zone 	EN 60079-0:2009, EN60079-15:2010, II 3 G Ex nA IIC T4 Gc, KEMA 07ATEX0145 X		
 for safety / from CSA and UL 	UL 60950-1, CSA C22.2 No. 60950-1		
 for emitted interference 	EN 61000-6-4 (Class B)		
• for interference immunity	61000-6-2		
MTBF	71 у		
standards, specifications, approvals / CE certificate of suitability / CE marking	Yes		
· ·			
	standards, specifications, approvals / hazardous environments		
certificate of suitability			
• IECEx	Yes; IEC 60079-0, IEC 60079-15, IECEx DEK 14.0025X, Ex nA IIC T4 Gc		
standards, specifications, approvals / other	EN 61000 6 2 EN 61000 6 4		
certificate of suitability	EN 61000-6-2, EN 61000-6-4 Yes		
Regulatory Compliance Mark (RCM)	Yes		
KC approval	Tes		
further information / internet-Links			
Internet-Link			
 to website: Selector TIA Selection Tool 	http://www.siemens.com/snst		
 to website: Industrial communication 	http://www.siemens.com/simatic-net		
 to website: Industry Mall 	https://mall.industry.siemens.com		
 to website: Information and Download Center 	http://www.siemens.com/industry/infocenter		
 to website: Image database 	http://automation.siemens.com/bilddb		
 to website: CAx-Download-Manager 	http://www.siemens.com/cax		
 to website: Industry Online Support 	https://support.industry.siemens.com		
security information			
security information	Siemens provides products and solutions with industrial security		
	functions that support the secure operation of plants, solutions,		
	machines, equipment and/or networks. They are important components in a holistic industrial security concept. With this in		
	mind, Siemens' products and solutions undergo continuous		
	development. Siemens recommends strongly that you regularly		
	check for product updates. For the secure operation of Siemens		
	products and solutions, it is necessary to take suitable preventive		
	action(e.g. cell protection concept) and integrate each component into a holistic, state-of-the-art industrial security concept. Third-		
	party products that may be in use should also be considered. For		
	more information about industrial security, visit		
	http://www.siemens.com/industrialsecurity. To stay informed about		
	product updates as they occur, sign up for a product-specific		
	newsletter. For more information, visit		
	http://support.automation.siemens.com. (V3.4)		

last modified: