

# INT-R

## MULTIFUNCTION EXPANDER FOR CARD / CHIP READERS

Extension module for INTEGRA control panels enabling proximity card readers and/or iButton chip readers to be connected to implement access control to and arming/disarming of the partition. The INT-R expander can interface with the INTEGRA and CA-64 alarm control panels.

### Features:

- support for two proximity card / iButton chip readers
- compatible with Wiegand 26 format readers
- relay to control electromagnetic door lock input for door status control
- input for door opening with a button capability to automatically open the door in case of fire alarm
- tamper input



## TECHNICAL DATA

|                                       |               |
|---------------------------------------|---------------|
| Environmental class                   | II            |
| Board dimensions                      | 140 x 68 mm   |
| Operating temperature range           | -10...+55 °C  |
| Supply voltage                        | 12 V DC ±15%  |
| Standby mode current consumption      | 110 mA        |
| Max. current consumption              | 150 mA        |
| Weight                                | 80 g          |
| Relay contacts rated load (resistive) | 5 A / 30 V DC |
| Maximum humidity                      | 93 ±3%        |



The actual appearance of the products may differ from the presented images. Product descriptions are provided in the web service for information purposes only.